



ALTAIR

Altair® FluxMotor® 2025

Motor Factory – Windings

General user information

Contents

| | | |
|----------|---|-----------|
| 1 | Winding design environment | 6 |
| 1.1 | Overview | 6 |
| 1.2 | Winding design area | 7 |
| 1.2.1 | Home page | 7 |
| 1.2.2 | Selection of sections | 8 |
| 1.2.3 | Information about Winding area GUI | 9 |
| 1.3 | Advice for use | 11 |
| 1.3.1 | Structural data - Validity domain | 11 |
| 1.3.2 | Layout of the winding – Winding connections | 13 |
| 2 | Classical winding design | 14 |
| 2.1 | Terminology – Illustration | 14 |
| 2.1.1 | Theoretical definition | 14 |
| 2.1.2 | Terminology – Application in Motor Factory | 14 |
| 2.2 | Classical winding architecture - Inputs | 15 |
| 2.2.1 | Overview – Definitions | 15 |
| 2.2.2 | Automatic mode | 16 |
| 2.2.2.1 | User input parameters | 16 |
| 2.2.2.2 | Building the winding architecture – Automatic mode – Main principles | 16 |
| 2.2.2.3 | Parallel paths | 17 |
| 2.2.3 | Easy mode | 18 |
| 2.2.3.1 | User input parameters | 18 |
| 2.2.3.2 | Building the winding architecture – Easy mode – Main principles | 18 |
| 2.2.3.3 | Number of layers | 19 |
| 2.2.3.4 | Coil pitch | 19 |
| 2.2.3.5 | Winding type | 20 |
| 2.2.4 | Advanced mode | 21 |
| 2.2.4.1 | User input parameters | 21 |
| 2.2.4.2 | Building the winding architecture – Advanced mode – Main principles | 21 |
| 2.2.4.3 | Pole distribution | 22 |
| 2.2.4.4 | Winding customization | 22 |
| 2.2.5 | Expert mode | 23 |
| 2.2.5.1 | User input parameters | 23 |
| 2.2.5.2 | Main principles | 23 |
| 2.2.5.3 | Build a coil with expert mode. | 25 |
| 2.2.5.4 | Coil layout in slot | 26 |
| 2.2.5.5 | Phase offset parameter | 27 |
| 2.2.5.6 | Winding direction for coils | 27 |
| 2.2.5.7 | Additional information | 28 |
| 2.3 | Classical coil design - Inputs | 29 |
| 2.3.1 | Overview - Definitions | 29 |
| 2.3.2 | Relevance of the slot filling | 34 |
| 2.3.3 | Slot filling illustrations – Circular shape type wire | 35 |
| 2.3.4 | Conductor grouping method illustrations - Circular shape type wire | 35 |
| 2.3.5 | Conductor grouping method illustrations - Rectangular shape type wire | 36 |
| 2.4 | Winding insulation design - Inputs | 37 |
| 2.4.1 | Overview - Definitions | 37 |
| 2.4.2 | Illustrations for circular shape type wire | 37 |
| 2.4.3 | Impregnation | 38 |
| 2.4.4 | Illustrations for rectangular shape type wire | 38 |

| | | |
|------------|--|-----------|
| 2.5 | End winding design of classical winding – Inputs | 39 |
| 2.5.1 | Overview - definitions | 39 |
| 2.5.2 | End-winding topology – U-Shape | 39 |
| 2.5.3 | End-winding topology – C shape | 40 |
| 2.5.4 | End-winding topology – Y shape | 41 |
| 2.6 | Calibration factors (Definition – Inputs) | 42 |
| 2.6.1 | Overview - Definitions | 42 |
| 2.6.2 | Illustrations | 42 |
| 2.6.3 | Warning - Negative end winding resistance with low value of X-Factors. | 43 |
| 2.7 | Potting design – Inputs | 44 |
| 2.7.1 | Overview - Definitions | 44 |
| 3 | Classical winding outputs | 45 |
| 3.1 | Characteristics | 45 |
| 3.1.1 | Winding | 45 |
| 3.1.2 | Winding factors (Fundamental) | 45 |
| 3.1.3 | Coil | 45 |
| 3.1.4 | Lengths | 46 |
| 3.1.5 | Areas in slot | 46 |
| 3.1.6 | Fill factors | 46 |
| 3.2 | Slot filling | 46 |
| 3.3 | Resistances | 47 |
| 3.3.1 | Resistances – Resistance at 20°C and at ref. temperature | 47 |
| 3.4 | Inductances | 47 |
| 3.5 | Masses and costs | 47 |
| 3.6 | Visualization of the winding architecture | 48 |
| 3.7 | Magneto-Motive Force analysis | 49 |
| 3.8 | Quality criteria | 50 |
| 3.8.1 | Winding factor | 50 |
| 3.8.2 | Slot star | 50 |
| 4 | Hairpin winding design | 51 |
| 4.1 | Differences with classical winding | 51 |
| 4.2 | Terminology – Illustration | 51 |
| 4.3 | Hairpin winding architecture - Inputs | 52 |
| 4.3.1 | Overview – Definitions | 52 |
| 4.3.2 | Automatic mode | 53 |
| 4.3.2.1 | User input parameters | 53 |
| 4.3.2.2 | Building the winding architecture – Automatic mode – Main principles | 53 |
| 4.3.3 | Easy mode | 54 |
| 4.3.3.1 | User input parameters | 54 |
| 4.3.3.2 | Building the winding architecture – Easy mode – Main principles | 54 |
| 4.3.4 | Advanced mode | 55 |
| 4.3.4.1 | User input parameters | 55 |
| 4.3.4.2 | Building the winding architecture – Advanced mode – Main principles | 55 |
| 4.3.5 | Expert mode | 56 |
| 4.3.5.1 | User input parameters | 56 |
| 4.3.5.2 | Main principles | 56 |
| 4.3.5.3 | Build a coil with expert mode | 57 |

| | | |
|------------|--|-----------|
| 4.4 | Hairpin coil design - Inputs | 59 |
| 4.4.1 | Overview - Definitions | 59 |
| 4.4.2 | Relevance of the slot filling | 60 |
| 4.5 | Hairpin winding insulation design - Inputs | 61 |
| 4.5.1 | Overview - Definitions | 61 |
| 4.5.2 | Illustrations for rectangular shape type wire | 61 |
| 4.6 | End winding design of hairpin winding – Inputs | 62 |
| 4.6.1 | Overview - definitions | 62 |
| 4.6.2 | End-winding topology – Y-Shape | 62 |
| 4.7 | Calibration factors definition - Inputs | 63 |
| 4.7.1 | Overview - Definitions | 63 |
| 4.8 | Potting design – Inputs | 63 |
| 4.8.1 | Overview - Definitions | 63 |
| 5 | Hairpin winding outputs | 64 |
| 5.1 | Characteristics | 64 |
| 5.1.1 | Winding | 64 |
| 5.1.2 | Winding factors (Fundamental) | 64 |
| 5.1.3 | Coil | 64 |
| 5.1.4 | Lengths | 65 |
| 5.1.5 | Areas in slot | 65 |
| 5.1.6 | Fill factors | 65 |
| 5.2 | Slot filling | 65 |
| 5.3 | Resistances | 65 |
| 5.3.1 | Resistances – Resistance at 20°C and at ref. temperature | 65 |
| 5.4 | Inductances | 65 |
| 5.5 | Masses and costs | 66 |
| 5.6 | Visualization of the winding architecture | 66 |
| 5.7 | Magneto-Motive Force analysis | 67 |
| 5.8 | Quality criteria | 67 |
| 5.8.1 | Winding factors | 67 |
| 5.8.2 | Slot star | 68 |
| 5.8.3 | Parallel paths | 69 |
| 5.8.4 | Voltage drop | 71 |
| 6 | Field Winding | 72 |
| 6.1 | Overview | 72 |
| 6.1.1 | Winding Architecture | 73 |
| 6.1.1.1 | Parallel paths | 73 |
| 6.1.2 | Winding – Coil | 74 |
| 6.1.3 | Winding – Insulation | 75 |
| 6.1.3.1 | Liner thickness adjustment via part definition | 76 |
| 6.1.4 | Winding – End Winding | 76 |
| 6.1.5 | Winding – Calibration factor | 77 |
| 7 | DC WINDING | 78 |
| 7.1 | Overview | 78 |
| 7.2 | Winding Architecture - Inputs | 79 |

| | | |
|----------|--|-----------|
| 7.2.1 | Overview – Definitions | 79 |
| 7.2.2 | Automatic mode | 80 |
| 7.2.2.1 | User input parameters | 80 |
| 7.2.2.2 | Building the winding architecture – Automatic mode – Main principles | 80 |
| 7.2.3 | Easy mode | 81 |
| 7.2.3.1 | User input parameters | 81 |
| 7.2.3.2 | Building the winding architecture – Easy mode – Main principles | 81 |
| 7.2.3.3 | Winding type | 82 |
| 7.2.3.4 | Plex | 82 |
| 7.2.3.5 | Coil connection | 83 |
| 7.2.4 | Advanced mode | 84 |
| 7.2.4.1 | User input parameters | 84 |
| 7.2.4.2 | Building the winding architecture – Advanced mode – Main principles | 84 |
| 7.2.5 | Winding Architecture – Outputs | 85 |
| 7.2.5.1 | Characterization - Winding | 85 |
| 7.2.5.2 | Characterization - Coil | 85 |
| 7.2.5.3 | Lengths | 85 |
| 7.2.5.4 | Areas in slot | 86 |
| 7.2.5.5 | Fill factors | 86 |
| 7.2.5.6 | Resistances | 86 |
| 7.2.5.7 | Inductances | 86 |
| 7.2.5.8 | Masses and costs | 87 |
| 7.2.5.9 | Visualization of the winding architecture | 87 |
| 8 | Choice of winding materials | 88 |

1 WINDING DESIGN ENVIRONMENT

1.1 Overview

In Motor Factory, two types of winding can be designed: Classical windings or hairpin winding types.
Note: Winding design environment also includes polyphase windings up to 15 phases. Most of the examples and images shown for classical winding are for a three-phase winding to facilitate comprehension and clarity, since it is the most widely used.

Here is the home page for designing both classical and hairpin winding.


| WINDING design area – Area dedicated to classical windings | |
|--|--|
| 1 | Selection of the STATOR subset: WINDING panel (Click on the icon WINDING) |
| 2 | Winding input parameter panel dedicated for designing of the winding (either classical or hairpin technology windings) |
| 3 | Buttons to select the winding type “classical or hairpin” (here classical winding is selected – Highlighted in blue). |
| 4 | Shortcuts to easily navigate in the output sections |

The following sections describe the GUI dedicated to the classical and hairpin winding design.
The sections 2 & 3 are dedicated to classical winding design whereas sections 4 & 5 concerns the hairpin winding design.

1.2 Winding design area

1.2.1 Home page

For both types of winding, whether classical or hairpin, the home page characteristics are the same. The following picture illustrates the main areas of the home page which is displayed for the classical winding.



WINDING design area – Classical winding - Overview

| | |
|--------|---|
| 1 | Selection of the STATOR subset: WINDING panel (Click on the icon WINDING) |
| 2 | All the required user inputs to define the winding are available in the "WINDING" panel (right part). |
| 3 | Selection of the classical winding design (Highlighted in blue) |
| 4 | Winding settings allow describing the winding architecture |
| 5 | Once a winding is defined, the corresponding results are automatically displayed in the form of a winding report. Visualization of the winding characteristics (inputs, settings, materials, etc) are possible. Scrollbars allow browsing the whole document rapidly and giving an overview of all the results. Using scrollbars, complete data can be accessed and visualized. |
| 6 | Shortcuts for displaying the corresponding section of the winding report. |
| 7 | A section scrolling bar allows choosing the section in which user inputs are defined. Scrolling selection bar where Winding architecture, Coil, Insulation, End-winding, X-Factor and Potting sections can be selected |
| 8 | Choice of the winding connection: Y (Wye or Star) or Δ (Delta). (Only available for 3-phase winding, polyphase winding is always connected in star connection). |
| 9 | Four modes of winding allow to define and build the winding architecture . |
| Auto | Automatic mode, used as default. |
| Easy | Easy mode, to choose solution among those FluxMotor® proposes. |
| Adv. | Advanced mode, to allow the user to define any specific input parameters. |
| Expert | Expert mode, to set the connection table. |
| 10 | User input parameter fields to enter the values according to the considered mode. |

Note: This usage mode is applied for hairpin winding environment as well.

1.2.2 Selection of sections

A scrolling selection bar helps to choose the section in which one can define the winding settings. The winding can be built step by step. One can access the different sections by clicking on the following buttons:

- “Winding” to build the winding architecture.
- “Coil” to set how the coil is defined and to see how the slots are filled.
- “Insulation” to define all the winding insulations.
- “End winding” to define the topology and dimensions of the end-windings.
- “X-Factor” to adjust phase resistance and end-winding inductance.
- “Potting” to define the topology and dimensions of the potting around the end-winding.


Note: “Potting” section is available only when the housing is defined with a frame (circular or square shape).

Scrolling selection bar – Winding environment

| | |
|---|--|
| 1 | Scrolling selection bar, where Winding, Coil, Insulation, End-winding, X-Factor and Potting sections can be selected |
| 2 | Section data representing shortcuts for analyzing the input and output parameters |
| 3 | Arrow symbol allows the user to scroll the bar to reach other sections (on the right or the left) when needed |
| 4 | The bar slides on the right to allow reaching Potting section |


Note: This mode of section selection is applied for hairpin winding environment as well.

1.2.3 Information about Winding area GUI




WINDING design area – Information about GUI. Example for a seven-phase winding.

| | |
|---|---|
| 1 | Shortcuts for displaying the corresponding section of the winding report. |
| 2 | In the current example, select “Layout” displays the layout of the winding. |
| 3 | Picture legends are available on the right part of the screen. |
| 4 | The legends can be folded right to save space: see below. |



Process to fold or unfold the legends of graphics

| | |
|---|--|
| 1 | Click on the blue band. |
| 2 | The legend is folded right: there is more space to analyze pictures. Once the legend is folded, it is possible to unfold it by clicking on the grey band. |



Process to manage visualization of phases on the picture

| | |
|---|---|
| 1 | All the legend items are checked. The corresponding phases and the slot section are displayed. (With the phase color and sign to indicate the orientation of the electrical current). |
| 2 | Only the Phase 7 is checked. All the other phases are no longer displayed along with the slot section. |

| | Slots | | | | | | | | | | | | | | | | | |
|----|-------|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|----|
| | 5 | 10 | 15 | 20 | 25 | 30 | 35 | 40 | 45 | 50 | 55 | 60 | 65 | 70 | 75 | 80 | 85 | 90 |
| 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 |
| 4 | 1 | 2 | 1 | 4 | 1 | 2 | 1 | 4 | 1 | 2 | 1 | 4 | 1 | 2 | 1 | 4 | 1 | 2 |
| 6 | 1 | 2 | 3 | 2 | 1 | 6 | 1 | 2 | 3 | 2 | 1 | 6 | 1 | 2 | 3 | 2 | 1 | 6 |
| 8 | | 2 | 1 | 4 | 1 | 2 | 1 | 8 | 1 | 2 | 1 | 4 | 1 | 2 | 1 | 8 | 1 | 2 |
| 10 | | | | | 5 | | | | | 10 | | | | | 5 | | | |
| 12 | | 2 | 3 | 4 | 1 | 6 | 1 | 4 | 3 | 2 | 1 | 12 | 1 | 2 | 3 | 4 | 1 | 6 |
| 14 | | | 1 | 2 | 1 | 2 | 7 | 2 | 1 | 2 | 1 | 2 | 1 | 14 | 1 | 2 | 1 | 2 |
| 16 | | | 1 | 4 | 1 | 2 | 1 | 8 | 1 | 2 | 1 | 4 | 1 | 2 | 1 | 16 | 1 | 2 |
| 18 | | | 3 | 2 | 1 | 6 | 1 | 2 | 9 | 2 | 1 | 6 | 1 | 2 | 3 | 2 | 1 | 18 |
| 20 | | | | | 5 | | | | | 10 | | | | | 5 | | | |
| 22 | | | | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 11 | 2 | 1 | 2 | 1 | 2 | 1 | 2 |
| 24 | | | | 4 | 1 | 6 | 1 | 8 | 3 | 2 | 1 | 12 | 1 | 2 | 3 | 8 | 1 | 6 |
| 26 | | | | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 13 | 2 | 1 | 2 | 1 | 2 |
| 28 | | | | | 1 | 2 | 7 | 4 | 1 | 2 | 1 | 4 | 1 | 14 | 1 | 4 | 1 | 2 |
| 30 | | | | | 5 | | | | | 10 | | | | | 15 | | | |
| 32 | | | | | 1 | 2 | 1 | 8 | 1 | 2 | 1 | 4 | 1 | 2 | 1 | 16 | 1 | 2 |
| 34 | | | | | | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 17 | 2 |
| 36 | | | | | | 6 | 1 | 4 | 9 | 2 | 1 | 12 | 1 | 2 | 3 | 4 | 1 | 18 |
| 38 | | | | | | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 |
| 40 | | | | | | | | | | | | | | | 5 | | | |
| 42 | | | | | | | 7 | 2 | 3 | 2 | 1 | 6 | 1 | 14 | 3 | 2 | 1 | 6 |
| 44 | | | | | | | 1 | 4 | 1 | 2 | 11 | 4 | 1 | 2 | 1 | 4 | 1 | 2 |
| 46 | | | | | | | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 |
| 48 | | | | | | | | 8 | 1 | 2 | 1 | 12 | 1 | 2 | 3 | 16 | 1 | 6 |
| 50 | | | | | | | | | | | | | | | | | | |
| 52 | | | | | | | 4 | 1 | 2 | 1 | 4 | 13 | 2 | 1 | 1 | 4 | 1 | 2 |
| 54 | | | | | | | | 9 | 2 | 1 | 6 | 1 | 2 | 3 | 2 | 1 | 18 | |
| 56 | | | | | | | | 1 | 2 | 1 | 4 | 1 | 14 | 1 | 8 | 1 | 2 | |
| 58 | | | | | | | | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | |
| 60 | | | | | | | | | | 10 | | | | | 15 | | | |
| 62 | | | | | | | | | | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 |
| 64 | | | | | | | | | | 2 | 1 | 4 | 1 | 2 | 1 | 16 | 1 | 2 |
| 66 | | | | | | | | | | 2 | 11 | 6 | 1 | 2 | 3 | 2 | 1 | 6 |
| 68 | | | | | | | | | | | 1 | 4 | 1 | 2 | 1 | 4 | 17 | 2 |
| 70 | | | | | | | | | | | | | | | 5 | | | |
| 72 | | | | | | | | | | | 1 | 12 | 1 | 2 | 3 | 8 | 1 | 18 |
| 74 | | | | | | | | | | | 2 | 1 | 2 | 1 | 2 | 2 | 1 | 2 |
| 76 | | | | | | | | | | | 4 | 1 | 2 | 1 | 4 | 1 | 2 | |
| 78 | | | | | | | | | | | | 6 | 13 | 2 | 3 | 2 | 1 | 6 |
| 80 | | | | | | | | | | | | | | | 5 | | | |


Combinations No. poles / No. slots for a 5-Phase machine

| | Slots | | | | | | | | | | | | |
|----|-------|----|----|----|----|----|----|----|----|----|----|----|----|
| | 7 | 14 | 21 | 28 | 35 | 42 | 49 | 56 | 63 | 70 | 77 | 84 | 91 |
| 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 |
| 4 | 1 | 2 | 1 | 4 | 1 | 2 | 1 | 4 | 1 | 2 | 1 | 4 | 1 |
| 6 | 1 | 2 | 3 | 2 | 1 | 6 | 1 | 2 | 3 | 2 | 1 | 6 | 1 |
| 8 | 1 | 2 | 1 | 4 | 1 | 2 | 1 | 8 | 1 | 2 | 1 | 4 | 1 |
| 10 | | 2 | 1 | 2 | 5 | 2 | 1 | 2 | 1 | 10 | 1 | 2 | 1 |
| 12 | | 2 | 3 | 4 | 1 | 6 | 1 | 4 | 3 | 2 | 1 | 12 | 1 |
| 14 | | | | | | | 7 | | | | | | |
| 16 | | 2 | 1 | 4 | 1 | 2 | 1 | 8 | 1 | 2 | 1 | 4 | 1 |
| 18 | | 2 | 3 | 2 | 1 | 6 | 1 | 2 | 9 | 2 | 1 | 6 | 1 |
| 20 | | | 1 | 4 | 5 | 2 | 1 | 4 | 1 | 10 | 1 | 4 | 1 |
| 22 | | | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 11 | 2 | 1 |
| 24 | | | 3 | 4 | 1 | 6 | 1 | 8 | 3 | 2 | 1 | 12 | 1 |
| 26 | | | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 13 |
| 28 | | | | | | | 7 | | | | | | |
| 30 | | | | 2 | 5 | 6 | 1 | 2 | 3 | 10 | 1 | 6 | 1 |
| 32 | | | | 4 | 1 | 2 | 1 | 8 | 1 | 2 | 1 | 4 | 1 |
| 34 | | | | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 |
| 36 | | | | 4 | 1 | 6 | 1 | 4 | 9 | 2 | 1 | 12 | 1 |
| 38 | | | | | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 |
| 40 | | | | | 5 | 2 | 1 | 8 | 1 | 10 | 1 | 4 | 1 |
| 42 | | | | | | | 7 | | | | | | |
| 44 | | | | 1 | 2 | 1 | 1 | 4 | 1 | 2 | 11 | 4 | 1 |
| 46 | | | | | 1 | 2 | 1 | 2 | 1 | 2 | 1 | 2 | 1 |
| 48 | | | | | | 6 | 1 | 8 | 3 | 2 | 1 | 12 | 1 |
| 50 | | | | | | 2 | 1 | 2 | 1 | 10 | 1 | 2 | 1 |
| 52 | | | | | | 2 | 1 | 4 | 1 | 2 | 1 | 4 | 13 |
| 54 | | | | | | 6 | 1 | 2 | 9 | 2 | 1 | 6 | 1 |
| 56 | | | | | | | 7 | | | | | | |
| 58 | | | | | | | 1 | 2 | 1 | 2 | 1 | 2 | 1 |
| 60 | | | | | | | 1 | 4 | 3 | 10 | 1 | 12 | 1 |
| 62 | | | | | | | 1 | 2 | 1 | 2 | 1 | 2 | 1 |
| 64 | | | | | | | 1 | 8 | 1 | 2 | 1 | 4 | 1 |
| 66 | | | | | | | | 2 | 3 | 2 | 11 | 6 | 1 |
| 68 | | | | | | | | 4 | 1 | 2 | 1 | 4 | 1 |
| 70 | | | | | | | | | | | | | |
| 72 | | | | | | | | 8 | 9 | 2 | 1 | 12 | 1 |
| 74 | | | | | | | | 2 | 1 | 2 | 1 | 2 | 1 |
| 76 | | | | | | | | 1 | 2 | 1 | 1 | 4 | 1 |
| 78 | | | | | | | | 3 | 2 | 1 | 1 | 6 | 13 |
| 80 | | | | | | | | 1 | 10 | 1 | 1 | 4 | 1 |

Combinations No. poles / No. slots for a 7-Phase machine

1.3.2 Layout of the winding – Winding connections

The representation of connections between coils and phases has been modified. The lines that collect incoming and outgoing connections are merged into a single line. This has been done to make polyphase winding diagrams easier to read. The picture below that illustrates the difference between the two representations.




2 CLASSICAL WINDING DESIGN

General information: In the software winding datasheet, the parameters written in blue correspond to user input parameters and the parameters written in black correspond to data resulting from computations.


2.1 Terminology – Illustration

2.1.1 Theoretical definition



| Slot composition | |
|------------------|--|
| 1 | Wire (also called strand). |
| 2 | Conductor, that also corresponds to a turn section (one conductor = one turn). A conductor is composed with one or several wires in parallel (wires in hand). |
| 2* | The hatched area corresponds to the conductor's useful area. Area which includes: the wires + insulation + free space. This is not the conductive area. |
| 3 | Coil, which is an assembly of several conductors (i.e. several turns per coil). |

2.1.2 Terminology – Application in Motor Factory



| Slot composition | |
|------------------|---|
| 1 | Wire (also called strand) |
| 2 | Conductor (also called bundle). That also corresponds to a turn section (one conductor = one turn). A conductor is composed with one or several wires in parallel (wires in hand). |
| 3 | Coil, which is an assembly of several conductors (i.e. several turns per coil). |

2.2 Classical winding architecture - Inputs

2.2.1 Overview – Definitions

The following inputs define the winding architecture


| Label | Symbol | Tooltip, note, formula |
|--------------------------|----------------------|--|
| Winding connection | Connect | Winding connection (Y – Wye or Δ - Delta) |
| Definition mode | * | Winding definition mode: Automatic, Easy, Advanced or Expert. See below section dedicated to the construction of the winding architecture |
| No. parallel paths | P_{paths} | Number of parallel paths (all modes). |
| Phase sequence | * | Phase sequence (all modes). |
| Coil pitch | τ_{coil} | Coil pitch = number of slot pitch between coil input and coil output (Easy mode / Advanced mode). |
| No. layers | N_{layers} | Number of layers – 1 or 2 |
| Winding type | * | Winding type: Lap, Concentric or manual. Note: "Manual" characterizes the "winding type" when the chosen "Winding mode" is "Expert mode" |
| No. Coils / pole / phase | q | Number of slots per pole and per phase. $q = \frac{\text{Number of slots}}{2p \times m}$ (p is the number of pole pairs and m is the number of phases) |

2.2.2 Automatic mode

2.2.2.1 User input parameters

| Label | Symbol | Tooltip, note, formula |
|--------------------|-------------|---------------------------------------|
| Phase sequence | * | Phase sequence (all modes). |
| No. parallel paths | P_{paths} | Number of parallel paths (all modes). |

2.2.2.2 Building the winding architecture – Automatic mode – Main principles



Building the winding architecture - **Automatic** mode

| | |
|---|--|
| 1 | Selection of Automatic mode for building the winding architecture. |
| 2 | Definition of the phase sequence i.e. the rotation direction of the Magneto-Motive Force (M.M.F): Clockwise or Counterclockwise (Clockwise or C. clockwise). The rotation direction is defined when facing the machine on the connection side. |
| 3 | Number of parallel paths. The possible numbers of parallel paths are automatically computed and proposed to the user. When the user chooses a number of parallel paths the connections on the winding scheme are automatically updated. See examples below. |
| 4 | Button to apply inputs. Pressing the enter key twice applies inputs too. |
| 5 | Button to restore default input values. Default values are those which define the winding architecture by using the automatic mode. |
| 6 | Icon to export winding data into a text file |

2.2.2.3 Parallel paths

1

INPUTS

No. parallel paths1

Phase sequenceClockwise

✓↺

2

INPUTS

No. parallel paths8

Phase sequenceClockwise

✓↺

Building the winding architecture – The number of parallel paths are represented in the winding scheme


| | |
|---|---|
| 1 | Example where the No. parallel paths is equal to 1. |
| 2 | Example where the No. parallel paths is equal to 8. |

2.2.3 Easy mode

2.2.3.1 User input parameters

| Label | Symbol | Tooltip, note, formula |
|--------------------|---------------------|---|
| No. Layers | N_{Layers} | Number of layers - 1 or 2 (Easy mode). |
| Coil pitch | | Coil pitch = number of slot pitch between coil input and coil output (Easy mode / Advanced mode). |
| Winding type | * | Winding type - Lap or Concentric (Easy mode / Advanced mode). |
| Phase sequence | * | Phase sequence (all modes). |
| No. parallel paths | P_{paths} | Number of parallel paths (all modes). |

2.2.3.2 Building the winding architecture – Easy mode – Main principles




Building the winding architecture - **Easy** mode

| | |
|---|--|
| 1 | Selection of the Easy mode for building the winding architecture. |
| 2 | Selection of coil pitch. The proposed solutions depend on the number of slots, the number of poles and the number of phases. Example 1: With 12 slots, 10 poles and 3 phases, only one solution is proposed: a tooth winding. Example 2: With 48 slots, 8 poles and 3 phases, two solutions are proposed: 5 or 6. For various possibilities, a list of solutions is proposed. |
| 3 | Selection of the number of layers. The proposed solutions depend on the number of slots, the number of poles and the number of phases. Example: With 12 slots, 10 poles and 3 phases, only one solution is proposed: 1 layer. The three possible cases are illustrated below. |
| 4 | Number of parallel paths. The possible numbers of parallel paths are automatically computed and proposed to the user. When the user chooses a number of parallel paths, the connections on the winding scheme are automatically updated. See examples in Auto mode chapter. |
| 5 | Selection of winding type: Concentric or Lap. Illustration of these two types of winding is given below. |
| 6 | Definition of the phase sequence i.e. the rotation direction of the Magneto-Motive Force (M.M.F): Clockwise or Counter clockwise. The rotation direction is defined when facing the machine on the connection side. |
| 7 | Icon to restore default input values. Default values are those which defined the winding architecture by using the automatic mode. |
| 8 | Icon to apply inputs. Pressing the enter key twice applies inputs too. |
| 9 | Icon to export winding data into a text file |

2.2.3.3 Number of layers

1



Definition mode


AutoEasyAdvExpert

INPUTS

| | |
|--------------------|------------|
| Coil pitch | 5 |
| No. layers | 1 |
| No. parallel paths | 1 |
| Winding type | Concentric |
| Phase sequence | Clockwise |

✓↺

2



Definition mode

AutoEasyAdvExpert

INPUTS

| | |
|--------------------|-----------|
| Coil pitch | 5 |
| No. layers | 2 |
| No. parallel paths | 1 |
| Winding type | Lap |
| Phase sequence | Clockwise |


✓↺

Building the winding architecture – The number of layers are represented in the winding scheme

| | |
|---|--|
| 1 | Example, where the No. layers is equal to 1. |
| 2 | Example, where the No. layers is equal to 2. |

2.2.3.4 Coil pitch

1



Coil pitch = 5

Definition mode


AutoEasyAdvExpert

INPUTS

| | |
|--------------------|-----------|
| Coil pitch | 5 |
| No. layers | 1 |
| No. parallel paths | 1 |
| Winding type | Lap |
| Phase sequence | Clockwise |

✓↺

2



Coil pitch = 6

Definition mode

AutoEasyAdvExpert

INPUTS

| | |
|--------------------|-----------|
| Coil pitch | 6 |
| No. layers | 1 |
| No. parallel paths | 1 |
| Winding type | Lap |
| Phase sequence | Clockwise |


✓↺

Building the winding architecture – Definition of the coil pitch
(N° Slot return coil) - (N° Slot Go coil)


| | |
|---|--|
| 1 | Example, where the coil pitch is equal to 5 - From slot 1 to slot 6 (6-1 = 5). |
| 2 | Example, where the coil pitch is equal to 6 - From slot 1 to slot 7 (7-1 = 6). |

2.2.3.5 Winding type

1



2



Definition mode

Auto Easy Adv. Expert

INPUTS

| | |
|--------------------|------------|
| Coil pitch | 6 |
| No. layers | 1 |
| No. parallel paths | 1 |
| Winding type | Concentric |
| Phase sequence | Clockwise |

☒ ☐

Definition mode

Auto Easy Adv. Expert

INPUTS

| | |
|--------------------|-----------|
| Coil pitch | 6 |
| No. layers | 1 |
| No. parallel paths | 1 |
| Winding type | Lap |
| Phase sequence | Clockwise |

☒ ☐


| Building the winding architecture – Definition of the winding type: Lap or Concentric | |
|---|---|
| 1 | Example for the Concentric winding type. |
| 2 | Example for the Lap winding type. |

2.2.4 Advanced mode

2.2.4.1 User input parameters

| Label | Symbol | Tooltip, note, formula |
|--------------------------|--------------------|---|
| Coil pitch | * | Coil pitch = number of slot pitch between coil input and coil output (Easy mode / Advanced mode). |
| Winding type | * | Winding type - Lap or Concentric (Easy mode / Advanced mode). |
| Pole distribution | * | Pole distribution – Per pole or Consequent (Advanced mode). |
| No. coils / pole / phase | CPP | Number of coils per pole and per phase (Advanced mode). |
| Phase sequence | * | Phase sequence (all modes). |
| No. parallel paths | P _{paths} | Number of parallel paths (all modes). |

2.2.4.2 Building the winding architecture – Advanced mode – Main principles




Building the winding architecture - **Advanced** mode


| | |
|----|---|
| 1 | Selection of the Advanced mode for building the winding architecture. |
| 2 | Selection of coil pitch. In advanced mode, the user must define this value. There is no proposed short list of solutions. The relevance of the winding architecture has to be verified by the user. |
| 3 | Definition of the number of coils per pole and per phase. |
| 4 | Definition of the pole distribution: Per pole or Consequent. See an illustration of the two-pole distribution below. |
| 5 | Number of parallel paths. The possible numbers of parallel paths are automatically computed and proposed to the user. When the user chooses a number of parallel paths, the connections on the winding scheme are automatically updated. See examples in Auto mode chapter. |
| 6 | Selection of winding type: Concentric or Lap. Illustration of these two types of winding is given in the Easy mode section. |
| 7 | Definition of the phase sequence i.e. the rotation direction of the Magneto-Motive Force (M.M.F): Clockwise or Counter clockwise. The rotation direction is defined, when the machine facing is towards the connection side |
| 8 | Icon to restore default input values. Default values are those which define the winding architecture by using the automatic mode. |
| 9 | Icon to apply inputs. Pressing the enter key twice applies inputs too. |
| 10 | Icon to export winding data into a text file |

2.2.4.3 Pole distribution

1



2



Definition mode

AutoEasyAdvExpert

INPUTS

| | |
|--------------------------|------------|
| Coil pitch | 5 |
| No. coils / pole / phase | 1 |
| Pole distribution | Per pole |
| No. parallel paths | 1 |
| Winding type | Concentric |
| Phase sequence | Clockwise |

✓↺

Definition mode

AutoEasyAdvExpert

INPUTS

| | |
|--------------------------|------------|
| Coil pitch | 6 |
| No. coils / pole / phase | 2 |
| Pole distribution | Consequent |
| No. parallel paths | 1 |
| Winding type | Concentric |
| Phase sequence | Clockwise |


✓↺

Building the winding architecture – Definition of the pole distribution: Per pole or Consequent

| | |
|---|---|
| 1 | Example for the Per pole winding type. |
| 2 | Example for the Consequent winding type. |

2.2.4.4 Winding customization

3



2

1

Definition mode

AutoEasyAdvExpert

INPUTS

| | |
|--------------------------|------------|
| Coil pitch | 10 |
| No. coils / pole / phase | 1 |
| Pole distribution | Per pole |
| No. parallel paths | 1 |
| Winding type | Concentric |
| Phase sequence | Clockwise |

✓↺

Building the winding architecture – Advanced mode

The relevance of the winding architecture must be verified by the user


| | |
|---|--|
| 1 | Selection of the Advanced mode for building the winding architecture. |
| 2 | The choice of the user is not limited by a list. Any integer value can be chosen for the Coil pitch. For example, in this case, 10 has been written. |
| 3 | The result is that there are slots without coils. The relevance of the winding architecture depends on the user. A quality criterion allows verifying this relevance. Note: The process allows only zero, one or two coils per slot. |

2.2.5 Expert mode

2.2.5.1 User input parameters


| Label | Symbol | Tooltip, note, formula |
|--------------------|---------------------|---|
| No. Layers | N_{Layers} | Number of layers - 1 or 2 (Easy mode). |
| Coil layout | * | Coil layout inside the slot – Full, Superimposed or Adjacent (Advanced mode). |
| No. duplications | * | Number of duplications (Advanced mode). |
| Phase sequence | * | Phase sequence (all modes). |
| No. parallel paths | P_{paths} | Number of parallel paths (all modes). |

2.2.5.2 Main principles




Building the winding architecture - Expert mode

| | |
|---|---|
| 1 | Selection of the Expert mode for building the winding architecture. |
| 2 | "Set values" means opening the dialog box to fill the connection table. See illustration below. |
| 3 | Number of parallel paths. The possible numbers of parallel paths are automatically computed and proposed to the user. When the user chooses a number of parallel paths, the connections on the winding scheme are automatically updated. See examples in Auto mode chapter. Note: The complete list of the possible numbers of parallel paths is proposed. Sometimes, the number of parallel paths can be greater than the number of possible duplications. In that case, the connection of the parallel paths is not displayed on the layout of the winding. See the illustration below. |
| 4 | Definition of the phase sequence i.e. the rotation direction of the Magneto-Motive Force (M.M.F): Clockwise or Counter clockwise. |
| 5 | Icon to apply inputs. Pressing the enter key twice applies inputs too. |
| 6 | Icon to restore default input values. Default values are those which define the winding architecture by using the automatic mode. |
| 7 | Icon to export winding data into a text file |




2.2.5.3 Build a coil with expert mode.




Building the winding architecture – Filling of the connection table

| | |
|---|--|
| 1 | Dialog box to define a coil with Expert mode |
| 2 | Selection of the number of layers. The solutions depend on the number of slots, the number of poles and the number of phases. Example: With 12 slots, 10 poles and 3 phases, only one solution is proposed: 1 layer. The three possible cases are illustrated in the Easy mode section. |
| 3 | Definition of the coil layout i.e. how the coil sections are distributed into the slot. The three possible choices are: <ul style="list-style-type: none"> • Full = At least one coil into one slot • Superimposed = At least two superimposed coils into one slot • Adjacent = At least two adjacent coils into one slot The solutions depend on the number of slots and the number of poles. Example 1: With 12 slots, 10 poles and 3 phases, two solutions are proposed: superimposed or adjacent. Note that in that case, only toothed winding is relevant. This corresponds to an adjacent coil layout. Example 2: With 48 slots, 8 poles and 3 phases, one solution is imposed: Full. |
| 4 | Definition of the number of duplications. This number is computed and proposed to the user. It depends on the number of slots and the number of poles. When the winding architecture to build is cut into several identical parts, the corresponding possible number of duplications are proposed (a short list). By selecting the number of duplications, the user must define only 1/n of the connection table. |
| 5 | Number of circuits to be duplicated represent the number of elementary circuits to be defined inside each sector to be duplicated. In this example 2 circuits are defined in the represented sector. This is why, there are 2 connection tables to be filled in. One for each circuit: Phase 1 – Circuit 1 and Phase 1 – Circuit 2 |
| 6 | Phase offset – See illustration below. |



| Building the winding architecture – Filling of the connection table | |
|---|---|
| 1 | Dialog box to define a coil with expert mode |
| 2 | The connection table(s) must be filled in. 1 or 2 according to the number of circuits to be represented inside the considered elementary sector. <ul style="list-style-type: none">• Indication of the slot number which contains the input end of the coil.• Define the coil layout in the slot.• Indication of the slot number which contains the output end of the coil.• Define the coil layout in the slot.• Then, another line is proposed to describe the next coil. |
| 3 | Display of the 3-Phase winding |
| 4 | Make the phase visible or not |
| 5 | Button to cancel action and close the panel. |
| 6 | Button for erasing everything in the connection table (<i>Erase connection table data</i>). |
| 7 | Button to apply inputs and close the panel. |

2.2.5.4 Coil layout in slot



| Building the winding architecture – Definition of coil layout | |
|---|--|
| 1 | Example where the coil layout is Full . |
| 2 | Example where the coil layout is Superimposed . |
| 3 | Example where the coil layout is Adjacent . |


2.2.5.5 Phase offset parameter



Building the winding architecture – Filling of the connection table – Phase offset

| | |
|---|---|
| 1 | Definition of the phase offset = number of slot pitch between each phase. |
| 2 | Make the phase visible or not. Note: All the phases are identical. Phases 2 and 3 are identical to Phase 1 and is displayed in the winding by considering the phase offset. |

2.2.5.6 Winding direction for coils




Orient the coils when defining the phase circuits

| | |
|---|---|
| 1 | Definition of a positive orientation of coil i.e., in the clockwise direction from the connection size (=ascending order of slot numbers) |
| 2 | Definition of a negative orientation of coil i.e., in the counterclockwise direction from the connection size (=descending order of slot numbers) |

2.2.5.7 Additional information

The real distribution of the parallel paths in the winding is taken into account for performing the tests. It wasn't the case informer versions. Hence, it wasn't possible to know how the parallel paths are distributed and sometimes this led to a error. This issue has been fixed.

From now on, one need to know how the parallel paths were distributed. To do that, in the expert mode, to define the connection table, the user can define the number of circuits to be duplicated and for that, he must fill in a connection table for each elementary parallel path.



| PHASE - CIRCUIT 1 | |
|-------------------|-------|
| Coil | Input |
| 1 | 1 |
| 2 | Full |


| PHASE - CIRCUIT 2 | |
|-------------------|-------|
| Coil | Input |
| 1 | 12 |
| 2 | Full |

Dialog box for defining the connection table while using the expert mode

| | |
|---|---|
| 1 | Number of duplications. See the definition in table above. |
| 2 | Number of circuits to be duplicated. See the definition in table above. |
| 3 | Representation of the two circuits inside the considered sector. |

Then, the list of possible number of parallel paths « No. parallel paths » adapts itself in function to the number of duplications « No. duplications » and the number of circuits to be duplicated « No. circuits to be duplicated ».

Here is the resulting layout of the winding architecture below. There are always 4 possible parallel paths. These circuits can be well connected.



Layout of the resulting winding architecture

Warning:
Concerning, the motors built with a previous version (before 2022.2) and for which the winding was initially defined with the expert mode, when they will open with the current version the user input « No. circuits to be duplicated » will be set automatically to 1 and only one parallel circuit is considered.


Important note: This modification is a problem for motors the number of parallel paths « No. parallel paths » of which is greater to the number of duplications « No. duplications. »

In that case, one has decided to modify the value of the « No. parallel paths » to make it take the value of the « No. duplications ».

Important note: This is done without any warning given to the user.


2.3 Classical coil design - Inputs

2.3.1 Overview - Definitions



Definition of the coil – Case of Circular wires

| | |
|---|---|
| 1 | Selection of the STATOR subset: WINDING panel (Click on the icon WINDING) |
| 2 | Coil settings allows the user to describe the coil composition (turns, wires, dimensions) and how to fill the slot. |
| 3 | Definition of the wire topology, Circular or Rectangular |
| 4 | Choice of the method to fill the slot: Three ways are allowed to fill the slot: Orthocyclic, Random, Layer. See below illustrations. |
| 5 | Choice of the method to group the elementary wires. Three ways allow to fill the slot: Grouped, Horizontal, Vertical. See below illustrations. |
| 6 | Description of the coil (turns, wires in hand) and dimensions of elementary wires + twist options |



Definition of the coil – Case of rectangular wires

| | |
|---|--|
| 1 | Selection of the STATOR subset: WINDING panel (Click on the icon WINDING) |
| 2 | Coil settings allows the user to describe the coil composition (turns, wires, dimensions) and how to fill the slot. |
| 3 | Definition of the wire topology, Circular or Rectangular |
| 4 | Choice of the method to group the elementary wires. Three ways allow to fill the slot: Horizontal, Vertical. See below illustrations. |
| 5 | Description of the coil (turns, wires in hand) and dimensions of elementary wires |

The following inputs define the coil and how is filled the slots

| Label | Symbol | Tooltip, note, formula |
|---------------------------|---------------|---|
| Wire topology | * | Wire topology, Circular or Rectangular. |
| Slot filling | * | Three ways are allowed to fill the slot: Orthocyclic, Random, Layer See below illustrations |
| Conductor grouping method | * | Three ways are allowed to fill the slot: Grouped, Horizontal, Vertical See below illustrations |
| No. turns per coil | Turns | Number of turns per coil. |
| No. wires in hand | Nwires | Number of wires in parallel in a conductor (per turn) i.e. number of wires in parallel in each conductor. |
| Wire diameter | ϕ_{wire} | Wire diameter (without insulation), for circular wire ⁽¹⁾ |
| Wire width | W_{wire} | Wire width (without insulation), for rectangular shape type wire |
| Wire height | H_{wire} | Wire height (without insulation), for rectangular shape type wire |
| Inter-wire space | w//w | Minimum distance between insulated wires to be considered for modelling inside the Flux® 2D environment. When there is no wire insulation, Inter-wire space represents the minimum distance between the bar wires ⁽²⁾ . |
| Twisted wires | * | The wires can be twisted inside the conductor. |
| Twisted conductors | * | The conductors can be twisted inside the slot. |

(1) Different ways are available to choose the wire diameter:

- Directly entering the value of the wire diameter (without insulation)
- Choose the diameter from the American Wire Gauge table in which available wire diameters are listed (without insulation)
- Choose the diameter from the Metric Wire Gauge table in which available wire diameters are listed (without insulation)

1

| COIL | |
|------------------------------------|-------|
| No. turns per coil | 12 |
| No. wires in hand | 10 |
| Wire diameter (mm) | 1.12 |
| Inter wire space (half value) (mm) | 0.005 |
| Twisted wires | No |
| Twisted conductors | No |

✓

2

| COIL | |
|--------------------------|-------|
| No. turns per coil | 12 |
| No. wires in hand | 10 |
| Wire diameter (mm) | 1.12 |
| Wire diameter (mm) | 0.005 |
| AWG - wire diameter (mm) | No |
| MWG - wire diameter (mm) | No |


✓

| | |
|---|--|
| 1 | Multiple choices with a scrolling selection bar for selecting the wire diameter |
| 2 | Three ways are available for defining the dimensions of the wire diameter: <ul style="list-style-type: none">• Write the value of the wire diameter or to select it from the two below tables:• American Wire Gauge table in which available wire diameters are listed (without insulation)• Metric Wire Gauge table in which available wire diameters are listed (without insulation) |

(2) Illustration of inter-wire space

This value is considered in Motor factory for computing the filling factor, and while exporting a model into Flux® environment (EXPORT area) for building the corresponding finite element model.

2



1

| COIL | |
|------------------------------------|-------|
| No. turns per coil | 12 |
| No. wires in hand | 10 |
| Wire diameter (mm) | 1.12 |
| Inter wire space (half value) (mm) | 0.005 |
| Twisted wires | No |
| Twisted conductors | No |

✓

| COIL | |
|------------------------------------|------|
| No. turns per coil | 12 |
| No. wires in hand | 10 |
| Wire diameter (mm) | 1.12 |
| Inter wire space (half value) (mm) | 0.1 |
| Twisted wires | No |
| Twisted conductors | No |

✓



Illustration of inter-wire space



| | |
|---|---|
| 1 | Default value for inter-wire space and the corresponding pictorial display. |
| 2 | Impact of a higher value for inter-wire space |

(3) Twisted conductors and wires

While defining the coil in the design / Winding area, it is possible to twist the wires inside the conductors between the forward and return sections of the coil. It is also possible to twist the conductors between the forward and return sections of the coil.


It is possible to twist both the wires inside the coil and the conductors between the forward and return sections of the coil. The four illustrations of what it is possible to do are presented below.






2.3.2 Relevance of the slot filling

When the number of wires are higher than allowed by the free space of the slot, the wires are grayed. This is to inform the user that the number of wires must be decreased.
In that case, the design of the winding is not possible; the machine cannot be built or tested.




Motor Factory Design environment icon and winding icon in the Stator section are colored in red. This means that a design fault exists, and must be corrected in the winding section of the design environment.



The tests cannot be performed; the tooltip message indicates that the slot filling is not valid, and that the user must modify the slot filling parameters to unlock the test.
At the same time, a warning message indicates that there is not enough space for the specified number of wires. The allowed number of wires are mentioned in comparison with the targeted ones.




2.3.3 Slot filling illustrations – Circular shape type wire




2.3.4 Conductor grouping method illustrations - Circular shape type wire


Case 1 – With an Orthocyclic slot filling



Case 2 – With a random slot filling




Case 3 – With a layer slot filling



(1) Vertical filling is only available for tooth windings (i.e. when the coil pitch = 1)


2.3.5 Conductor grouping method illustrations - Rectangular shape type wire

Example 1



Note: Vertical filling is only available for tooth windings (i.e. when the coil pitch = 1)

Example 2 with a tooth winding (i.e. the coil pitch = 1)



2.4 Winding insulation design - Inputs

2.4.1 Overview - Definitions

Here are all the available insulation types.

| Label | Symbol | Tooltip, note, formula |
|-----------------------|--------|---|
| Wire | * | Insulation thickness of the wire |
| Conductor | * | Insulation thickness of the conductor. Available only for rectangular shape type wire. See below illustration. |
| Coil | * | Insulation thickness of the coil. Available only for rectangular shape type wire. See below illustration. |
| Liner | * | Insulation thickness of the liner |
| Phase separator | * | Insulation thickness of the phase separator |
| Impregnation | * | Insulation spread inside the slot |
| Impregnation goodness | * | Quality of impregnation (percentage of winding impregnation) |

2.4.2 Illustrations for circular shape type wire





Illustration of winding insulation for circular shape type wire

| | |
|---|--|
| 1 | Insulation thickness of the wire |
| 2 | Insulation thickness of the liner |
| 3 | Insulation thickness of the phase separator |
| 4 | Wedge to close the slot and maintain the winding inside. It is a part of the slot insulation. However, when needed, the wedge must be defined in the slot topology configuration and not in the insulation settings of the winding area. |

2.4.3 Impregnation



| INSULATION | |
|---------------------------|-----------|
| Wire (mm) | 4.789 E-2 |
| Conductor (mm) | - |
| Coil (mm) | - |
| Liner (mm) | 0.25 |
| Phase separator (mm) | 1.0 |
| Impregnation | No |
| Impregnation goodness (%) | No |

| INSULATION | |
|---------------------------|-----------|
| Wire (mm) | 4.789 E-2 |
| Conductor (mm) | - |
| Coil (mm) | - |
| Liner (mm) | 0.25 |
| Phase separator (mm) | 1.0 |
| Impregnation | Yes |
| Impregnation goodness (%) | 90.0 |

Illustration of winding impregnation in slot

| | |
|---|--|
| 1 | Winding without impregnation. The surface of the slot's free area is white. |
| 2 | Winding with impregnation. The free area of the slot is colored (light yellow). The impregnation goodness is defined by indicating the ratio between the volumes of impregnation material and air bubbles to be considered. |

2.4.4 Illustrations for rectangular shape type wire




Illustration of winding insulation for rectangular shape type wire

| | |
|---|--|
| 1 | Insulation thickness of the wire |
| 2 | Insulation of conductors. This is available only for rectangular shape type wire when the conductor (i.e. the elementary group of wires in hand) has a rectangular outer shape. |
| 3 | Insulation of coils. This is available only for rectangular shape type wire when the coil (i.e. the group of turns inside a layer) has a rectangular outer shape. |
| 4 | Insulation thickness of the liner |
| 5 | Insulation thickness of the phase separator |
| 6 | Wedge to close the slot and maintain the winding inside. It is a part of the slot topology configuration and not in the insulation settings of the winding area. |

2.5 End winding design of classical winding – Inputs

2.5.1 Overview - definitions


This part characterizes the end-winding and the resulting conductor dimensions.

For additional information refer to the sections dedicated to the coil and conductor settings and End-winding topology.

| Label | Symbol | Tooltip, note, formula |
|---------------------------|--------|--|
| End-winding topology | * | End-winding topology: U-shape, C-shape or Y-shape. |
| C.S. total extension | * | Connection side total extension. |
| C.S. straight extension | * | Connection side straight extension |
| Axial overall length | * | Axial overall length. Length between the two extremities of the winding i.e. between connection side and opposite connection side. |
| O.C.S. total extension | * | Opposite connection side total extension. |
| O.C.S. straight extension | * | Opposite connection side straight extension. |
| Total conductor length | * | Total conductor length. |
| Mean turn length | * | Mean turn length. |
| Coil connection length | * | Additional length corresponding to the connections between coils. |

2.5.2 End-winding topology – U-Shape

Topology available for all the 3 winding architectures




Building the winding – End-winding topology and dimensions
Case of the U-shape End-winding

| | |
|---|--|
| 1 | Selection of the END-WINDING tab. |
| 2 | Selection of the U-Shape end-winding case. |
| 3 | Straight extension of the U-Shape end-winding topology = User input parameter. |
| 4 | Total extension of the U-Shape end-winding topology = User input parameter. |
| 5 | Definition of the connection side straight extension (ref. 3). |
| 6 | Definition of the opposite connection straight extension (ref. 3). |
| 7 | Definition of the connection side total extension (ref. 4). |
| 8 | Definition of the opposite connection side total extension (ref. 4). |

2.5.3 End-winding topology – C shape

Topologies available for all winding architecture




Building the winding – End-winding topology and dimensions
Case of the C-shape End-winding

| | |
|---|---|
| 1 | Selection of the END-WINDING tab. |
| 2 | Selection of the C-Shape end-winding topology. |
| 3 | Straight extension of the C-Shape end-winding topology = User input parameter. |
| 4 | Total extension of the C-Shape end-winding topology = Computation result deduced from topology characteristics. |
| 5 | Definition of the connection side straight extension = User input (ref. 3). |
| 6 | Definition of the opposite connection straight extension = User input (ref. 3). |
| 7 | Definition of the connection side total extension = Deduced result (ref. 4). |
| 8 | Definition of the opposite connection side total extension = Deduced result (ref. 4). |

2.5.4 End-winding topology – Y shape

This topology is available only with two layers and superimposed coil layout.



Building the winding – End-winding topology and dimensions
Case of the Y-shape End-winding

| | |
|---|--|
| 1 | Selection of the END-WINDING tab. |
| 2 | Selection of the Y-Shape end-winding case. |
| 3 | Straight extension of the Y-Shape end-winding topology = User input parameter. |
| 4 | Total extension of the Y-Shape end-winding topology = User input parameter. |
| 5 | Definition of the connection side straight extension (ref. 3). |
| 6 | Definition of the opposite connection straight extension (ref. 3). |
| 7 | Definition of the connection side total extension (ref. 4). |
| 8 | Definition of the opposite connection side total extension (ref. 4). |

2.6 Calibration factors (Definition – Inputs)

2.6.1 Overview - Definitions

| Label | Symbol | Tooltip, note, formula |
|-------------------|--------|---|
| Resistance factor | * | Setting of the “Resistance factor”: It allows modifying the computation result of resistance. Thus, the resulting phase resistance value is considered. |
| Inductance factor | * | Setting of the “Inductance factor”. It allows modifying the computation result of end-winding inductance. Thus, the resulting end-winding inductance value is considered. |
| Ref. temperature | * | <p>The reference temperature: First, the resistance values are computed by considering a temperature equal to 20°C. However, the user can also define his own reference temperature to compute the corresponding phase resistance and Line-Line resistance values.</p> <p>Note: This reference temperature is used only in the winding design environment. The test temperatures are defined in the test settings (refer to TEST chapter).</p> |

2.6.2 Illustrations

Building the winding – X-Factor = Calibration factors

| | |
|---|--|
| 1 | Selection of the X-FACTOR section. |
| 2 | Setting of the “Resistance factor”. It allows adjusting computation result of resistance. Thus, the resulting phase resistance value is considered. |
| 3 | Setting of the “Inductance factor”. It allows modifying the computation result of end-winding inductance. Thus, the resulting end-winding inductance value is considered. |
| 4 | <p>The reference temperature:</p> <p>First, resistance values are computed by considering a temperature equal to 20°C (5). However, the users can also define their own reference temperature to compute the corresponding phase resistance and Line-Line resistance values.</p> |
| 5 | Resistance values for a reference temperature equal to 20°C. |

2.6.3 Warning - Negative end winding resistance with low value of X-Factors.

Here are a few explanations for this issue:

This issue has been introduced while considering the solid conductors inside the slot. Since the solid conductors are considered, the corresponding resistance (in the straight part of the machine) is deduced from the material properties and the size of the wires.

With $X\text{-factor}=1$, we have $(R_{\text{phase } 0}) = (R_{\text{straight } 0}) + (R_{\text{end winding } 0})$

- $R_{\text{phase } 0}$ is the initial value of the phase resistance (with $X\text{-Factor} = 1$)
- $R_{\text{Straight } 0}$ is the initial value of the phase resistance in the straight part of the machine (with $X\text{-Factor} = 1$)
- $R_{\text{end winding } 0}$ is the initial value of the phase resistance in the straight part of the machine (with $X\text{-Factor} = 1$)

With $X\text{-factor}\neq 1$, we have $(R_{\text{phase } 1}) = (R_{\text{straight } 1}) + (R_{\text{end winding } 1})$

- $R_{\text{phase } 1}$ is the initial value of the phase resistance (with $X\text{-Factor} \neq 1$)
- $R_{\text{Straight } 1}$ is the initial value of the phase resistance in the straight part of the machine (with $X\text{-Factor} \neq 1$)
- $R_{\text{end winding } 1}$ is the initial value of the phase resistance in the straight part of the machine (with $X\text{-Factor} \neq 1$)

The target is to get the following results:

$$(R_{\text{phase } 1}) = X\text{Factor} \times (R_{\text{straight } 0})$$

With

$$(R_{\text{straight } 1}) = (R_{\text{straight } 0})$$

This leads to the value for the end winding resistance:

$$(R_{\text{end winding } 1}) = X\text{Factor} \times (R_{\text{straight } 0} + R_{\text{end winding } 0}) - (R_{\text{straight } 0})$$

$$(R_{\text{end winding } 1}) = R_{\text{straight } 0} \times (X\text{Factor} - 1) + X\text{Factor} \times (R_{\text{end winding } 0})$$

When $X\text{-Factor}$ is very low, the end winding resistance can be negative.


We will reconsider how to apply the calibration factor to the winding resistance. Perhaps this will lead to applying the $X\text{-Factor}$ only to the end winding and the winding connections not to then straight part.

Note that this problem doesn't impact the phase resistance value, nor the resulting computations, like the total Joule losses in the winding. (ref.: FXM-16113).

2.7 Potting design – Inputs

2.7.1 Overview - Definitions

“Potting” section is available only when the housing is defined with a frame (circular or square shape).



Building the winding – Definition of the topology and dimensions of the potting around the end-winding

| | |
|---|--|
| 1 | Selection of the Potting section. |
| 2 | Button to define a potting with only radial contact. |
| 3 | Button to define a potting with radial and axial contacts. |
| 4 | Extension of potting with radial contact only. |
| 5 | Button to apply inputs. Apply is needed to modify the characteristics. |

3 CLASSICAL WINDING OUTPUTS

3.1 Characteristics

3.1.1 Winding

| Label | Symbol | Tooltip, note, formula |
|--------------------------|---------------------|---|
| No. phases | m | Number of phases |
| No. poles | p | Number of rotor pole pairs. $2p$ = number of poles. |
| No. slots | Nslots | Number of stator slots |
| No. parallel paths | P _{paths} | Number of parallel paths (all modes). |
| No. Layers | N _{layers} | Number of layers - 1 or 2. |
| Coil layout | * | Coil layout inside the slot – Full, Superimposed or Adjacent. |
| Winding connection | Connect | Winding connection (Y – Wye or Δ - Delta) |
| Winding type | * | The winding type: Lap, Concentric or manual. Note: "Manual" characterizes the "winding type" when the chosen "Winding mode" is "Expert mode" |
| Pole distribution | * | Pole distribution – "Per pole" or "Consequent" Accessible via "Advanced mode". |
| No. slots / pole / phase | q | Number of slots per pole and per phase. $q = \frac{N_{slots}}{2p \times m}$ (p is the number of pole pairs and m the number of phases) |
| Pole pitch | τ_{pole-z} | $\tau_{pole-z} = \frac{N_{slots}}{2p}$ (Nslots = number of slots and p= number of pole pairs) |
| Phase sequence | * | Phase sequence i.e. rotation direction of the Magneto-Motive Force (M.M.F.): Clockwise or Counterclockwise (C. Clockwise). The rotation direction is defined when facing the machine on the connection side. |
| No. coils / pole / phase | CPP | Number of coils per pole per phase (output data). As an output data, CPP is deduced from the analysis of the connection table. It is also a user input available in the advanced mode. |
| Coil pitch | τ_{coil} | Number of slot pitch between coil input and coil output (Easy mode and Advanced mode). |

3.1.2 Winding factors (Fundamental)

Only winding factors corresponding to the fundamental signals are listed below.

| Label | Symbol | Tooltip, note, formula |
|---------------------|-------------|--|
| Winding factor | K_W | Winding factor: $K_W = K_{Dist} \times K_{Pitch} \times K_{Skew}$ |
| Distribution factor | K_{Dist} | Distribution factor. |
| Pitch factor | K_{Pitch} | Pitch factor. |
| Skew factor | K_{Skew} | Note: Skew factor is computed when the skewing of the stator slots is considered. Without slot skewing this factor is always equal to 1. |

3.1.3 Coil

| Label | Symbol | Tooltip, note, formula |
|-------------------------------|-------------|--|
| No. turns per coil | Turns | Number of turns per coil. |
| No. turns in series per phase | N_{turns} | Number of turns in series per phase $N_{turns} = \frac{N_{coils}}{2 \times P_{paths}}$ |
| No. conductors per phase | N_{cond} | Number of conductors per phase = total number of conductors $N_{coils} = 2 \times (q \times 2 \times p \times Turns)$ Where p is the number of pole pairs and q is the number of slots per pole per phase. |

3.1.4 Lengths

| Label | Symbol | Tooltip, note, formula |
|------------------------|--------|--|
| Total conductor length | * | Total conductor length. |
| Mean turn length | * | Mean turn length. |
| Coil connection length | * | Additional length corresponding to the connections between coils. |
| Axial overall length | * | Axial overall length. Length between the two extremities of the winding i.e. between connection side and opposite connection side. |

3.1.5 Areas in slot

| Label | Symbol | Tooltip, note, formula |
|---------------------------|-----------------|---|
| Conductive area | $A_{CondSlot}$ | Conductive area inside one slot. One considers the slots of the machine where the number of coils are maximum. $A_{CondSlot} = A_{Cond} \times Turns$ |
| Conductor conductive area | A_{Cond} | $A_{Cond} = N_{wires} \times A_{wire}$ This area allows to compute the current density. |
| Wire conductive area | A_{wire} | Wire area (without insulation). |
| Slot area | A_{slot} | Slot area. |
| Insulation area | $A_{InsulSlot}$ | Insulation area inside one slot. One considers the slots of the machine where the number of coils are maximum. |
| Free area | A_{Free} | $A_{Free} = A_{slot} - A_{CondSlot} - A_{InsulSlot}$ |

3.1.6 Fill factors

| Label | Symbol | Tooltip, note, formula |
|-------------------|--------|---|
| Gross fill factor | * | Gross fill factor. Occupancy rate of the slot (conductive area only). $\frac{Conductor\ conductive\ area}{Slot\ area} \times 100$ |
| Net fill factor | * | Net fill factor. Occupancy rate of the slot (conductive area + insulation area). $\frac{Conductor\ conductive\ area + insulation\ area}{Slot\ area} \times 100$ |

3.2 Slot filling

The slot filling result gives the user a realistic view of the filling of the slot in function of the setting options. For additional information, please refer to the section 2.3 Classical coil design - Inputs.

3.3 Resistances

3.3.1 Resistances – Resistance at 20°C and at ref. temperature

| Label | Symbol | Tooltip, note, formula |
|---|--------|------------------------|
| Phase resistance | * | Phase resistance |
| Line-Line resistance | * | Line-Line resistance |
| Winding straight part resistance | * | |
| End-winding resistance | * | |
| Connection side end-winding resistance | * | |
| Opposite connection side end-winding resistance | * | |
| | | |

Note 1: The reference temperature is a user input parameter defined in the winding – X-Factor tab.

Note 2: The connection side end-winding resistance considers the additional length corresponding to the connection between coils.

3.4 Inductances


| Label | Symbol | Tooltip, note, formula |
|--------------------|--------|--|
| End winding | * | Total end winding inductance (including the two sides of the machine). |
| C.S. end winding | * | Connection side end winding inductance. |
| O.C.S. end winding | * | Opposite connection side end winding inductance. |

3.5 Masses and costs


For additional information, refer to the sections dedicated to the coil and conductor settings and End-winding topology.

| Label | Symbol | Tooltip, note, formula |
|----------------------------|--------|---|
| Total | * | Total winding mass. |
| Electric conductor | * | Conductive part mass. |
| Total insulation | * | Total winding insulation mass (wire + conductor + coil insulation + liner + phase separator). |
| Wire insulation | * | Wire insulation. |
| Conductor insulation | * | Conductor insulation. |
| Coil insulation | * | Coil insulation. |
| Liner insulation | * | Liner insulation. |
| Phase separator insulation | * | Phase separator insulation. |
| Impregnation insulation | * | Impregnation insulation |
| C.S. potting | * | Connection Side potting |
| O.C.S. potting | * | Opposite Connection Side potting |
| Wedge insulation | * | Wedge insulation, only when the slot topology contains a wedge |

3.6 Visualization of the winding architecture




3.7 Magneto-Motive Force analysis



WINDING design area

| | |
|---|--|
| 1 | Select the spatial representation of the Magneto-Motive Force (M.M.F.) |
| 2 | Check the curves to display. Sum of phases M.M.F or M.M.F. provided by each phase. Note: Superimposition of harmonics is possible only if one or several harmonics have been selected. See explanation below. |
| 3 | Visualize the harmonic list of the M.M.F. |
| 4 | Select the phase and make slide the M.M.F. signal. That shows the direction of rotation of the M.M.F... This illustrates the relevance of the phase sequence (user input). |
| 5 | Mechanical angle or slot number can be chosen for the X-axis. |
| 6 | Select one or several harmonics to superimpose with the original M.M.F. signal. |



Superimposition of harmonics to original M.M.F. signal


| | |
|---|---|
| 1 | Select the spatial representation of the Magneto-Motive Force (M.M.F.). |
| 2 | Check the curves to display. Sum of phases for example. |
| 3 | Check Harmonics. The harmonics previously selected in the M.M.F. harmonic table are superimposed with the original M.M.F. signal. |
| 4 | The selected phase is equal to 0. |

3.8 Quality criteria

3.8.1 Winding factor

1

Winding factors - Harmonic analysis



2

Winding factors

1


Select the winding factor bar-graph.

2

Checking the different winding factors allows visualizing the corresponding bar graph.
Note: Skew factor is computed when the skewing of the stator slots is considered. Without slot skewing this factor is always equal to 1.

3.8.2 Slot star

Slot star




Star slot. Example for 5-Phase machine

1

The Slot star represents the total vector summation of voltages at the ends of each coil

Proprietary Information of Altair Engineering

 **ALTAIR**

4 HAIRPIN WINDING DESIGN

Note: In the software winding datasheet, the parameters written in blue correspond to user input parameters and the parameters written in black correspond to data resulting from computations.


4.1 Differences with classical winding

The design of Hairpin winding type meet some limitations compared to the classical winding:

- Only three-phase winding is considered.
- Only integer number of slots per pole and per phase are allowed (fractional number are forbidden)
- A coil corresponds to one hairpin and not to an association of hairpins and back connections in serial.
- The hairpin which are associated in serial (thanks to back connections) are called parallel path or elementary coil.
- The number of turns in series per phase is defined by the number of conductors per layer, the number of layers and the number of parallel paths.
- Number of wires in hand is imposed to 1.
- Wire shape can be rectangular only.
- Insulation for conductors and coils are not available (please refer to the definition of coils and conductors)
- End winding shape can be Y shape only.
- New results of quality criteria dedicated to hairpin winding are available:
 - . Current balance for parallel paths
 - . Voltage drops between conductors.
- X-factor section gives an access to the inputs of the results “Conductor voltage drop.”

All these points are described in the following sections.

4.2 Terminology – Illustration



| Slot composition | |
|------------------|--|
| 1 | Conductor (also called bundle). That also corresponds to a turn section (one conductor = one turn). For hairpin winding type, a conductor is composed with only one wire (one wire in hand). |
| 2 | A coil which is an assembly of several conductors (i.e. several turns per coil). |

4.3 Hairpin winding architecture - Inputs

4.3.1 Overview – Definitions

The following inputs define the winding architecture


| Label | Symbol | Tooltip, note, formula |
|--------------------------|--------------|--|
| Winding connection | Connect | Winding connection (Y – Wye or Δ - Delta) |
| Definition mode | * | Winding definition mode: Automatic, Easy, Advanced or Expert. See below section dedicated to the construction of the winding architecture |
| No. layers | N_{layers} | Number of layers – 1 or 2 |
| No. conductors per layer | N_{cond} | Number of conductors per layer (only even number proposed) |
| No. parallel paths | P_{paths} | Number of parallel paths. |
| Phase sequence | * | Phase sequence (all modes). |
| Layer shift | * | The layer shift is defined by a number of slot pitches (Only available with 2 layers) |

4.3.2 Automatic mode

4.3.2.1 User input parameters

| Label | Symbol | Tooltip, note, formula |
|--------------------------|--------------|-----------------------------------|
| No. layers | N_{layers} | Number of layers – 1 only |
| No. conductors per layer | N_{cond} | Number of conductors per layer |
| No. parallel paths | P_{paths} | Number of parallel paths (1 or 2) |
| Phase sequence | * | Phase sequence |

4.3.2.2 Building the winding architecture – Automatic mode – Main principles



Building the winding architecture - Automatic mode


| | |
|---|--|
| 1 | Selection of Automatic mode for building the winding architecture. |
| 2 | Number of layers - 1 is the only value available for this mode |
| 3 | Number of conductors per layer, must be even and limited to 30. |
| 4 | Number of parallel paths. The possible numbers of parallel paths are automatically computed and proposed to the user, 2 is the maximum proposed value according to the used hairpin pattern. When the user chooses a number of parallel paths the connections on the winding scheme are automatically updated. |
| 5 | Definition of the phase sequence i.e. the rotation direction of the Magneto-Motive Force (M.M.F): Clockwise or Counter clockwise. The rotation direction is defined when facing the machine on the connection side. The phase sequence is set to clockwise and cannot be modified in the current version (grayed field). |
| 6 | Button to apply inputs. Pressing the enter key twice applies inputs too. |
| 7 | Button to restore default input values. Default values are those which define the winding architecture by using the automatic mode. |
| 8 | Icon to export winding data into *.txt or *.xlsx files. |
| 9 | Icon to export hairpin winding connection table into a *.xlsx file. This file can be shared and reloaded in another FluxMotor® session. |

4.3.3 Easy mode

4.3.3.1 User input parameters

| Label | Symbol | Tooltip, note, formula |
|--------------------------|-------------|--|
| No. Layers | * | Number of layers (1 or 2) |
| No. conductors per layer | * | No. conductors per layer |
| Layer shift | * | Layer shift in number of slot pitch (Only available with 2 layers) |
| No. parallel paths | P_{paths} | Number of parallel paths (1 or 2) |
| Phase sequence | * | Phase sequence |

4.3.3.2 Building the winding architecture – Easy mode – Main principles



Building the winding architecture - **Easy** mode


| | |
|----|--|
| 1 | Selection of the Easy mode for building the winding architecture. |
| 2 | Selection of the number of layers. The number of layers are limited to 2. |
| 3 | Number of conductors per layer, it must be even and limited to 30. |
| 4 | The layer shift is defined by a number of slot pitch. It cannot exceed the number of slots per pole and per phase. (Only available with 2 layers). |
| 5 | Number of parallel paths. The possible numbers of parallel paths are automatically computed and proposed to the user, 2 is the maximum value proposed according to the considered hairpin pattern. When the user chooses several parallel paths the connections on the winding scheme are automatically updated. |
| 6 | Definition of the phase sequence i.e. the rotation direction of the Magneto-Motive Force (M.M.F): Clockwise or Counter clockwise. The rotation direction is defined when facing the machine on the connection side. The phase sequence is set to clockwise and cannot be modified in the current version (grayed field). |
| 7 | Button to apply inputs. Pressing the enter key twice applies inputs too. |
| 8 | Button to restore default input values. Default values are those which define the winding architecture by using the automatic mode. |
| 9 | Icon to export winding data into *.txt or *.xlsx files. |
| 10 | Icon to export hairpin winding connection table into a *.xlsx file. This file can be shared and reloaded in another FluxMotor® session. |

4.3.4 Advanced mode

4.3.4.1 User input parameters

| Label | Symbol | Tooltip, note, formula |
|--------------------------|-------------|--|
| No. Layers | * | Number of layers (1 or 2) |
| No. conductors per layer | * | Number of conductors per layer |
| Layer shift | * | Layer shift in number of slot pitch (Only available with 2 layers) |
| No. parallel paths | P_{paths} | Number of parallel paths (1 or 2) |
| Phase sequence | * | Phase sequence |

4.3.4.2 Building the winding architecture – Advanced mode – Main principles



Building the winding architecture - **Advanced** mode


| | |
|----|--|
| 1 | Selection of the Advanced mode for building the winding architecture. |
| 2 | Selection of the number of layers. The number of layers are limited to 2. |
| 3 | Number of conductors per layer, it must be even and limited to 30. |
| 4 | The layer shift is defined by the number of slot pitch. It cannot exceed the number of slots per pole and per phase. (Only available with 2 layers). |
| 5 | Number of parallel paths. The possible numbers of parallel paths are automatically computed and proposed to the user, 2 is the maximum value proposed according to hairpin pattern used. When the user chooses several parallel paths. The connections on the winding scheme are automatically updated. |
| 6 | Definition of the phase sequence i.e. the rotation direction of the Magneto-Motive Force (M.M.F): Clockwise or Counter clockwise. The rotation direction is defined when facing the machine on the connection side. The phase sequence is set to clockwise and cannot be modified in the current version (grayed field). |
| 7 | Button to apply inputs. Pressing the enter key twice applies inputs too. |
| 8 | Button to restore default input values. Default values are those which define the winding architecture by using the automatic mode. |
| 9 | Icon to export winding data into *.txt or *.xlsx files. |
| 10 | Icon to export hairpin winding connection table into a *.xlsx file. This file can be shared and reloaded in another FluxMotor® session. |

4.3.5 Expert mode

4.3.5.1 User input parameters

| Label | Symbol | Tooltip, note, formula |
|------------------------------|---------------------|--|
| No. Layers | N_{Layers} | Number of layers (1 or 2) |
| No. conductors per layer | * | Number of conductors per layer (even) |
| No. slots/pole/phase to fill | * | Number of slots per pole and per phase to fill |
| Phase sequence | * | Phase sequence (all modes) |

4.3.5.2 Main principles



Building the winding architecture - Expert mode

| | |
|---|--|
| 1 | Selection of the Expert mode for building the winding architecture. |
| 2 | "Set values" means opening the dialog box to fill the connection table. See illustration below. |
| 3 | Definition of the phase sequence i.e. the rotation direction of the Magneto-Motive Force (M.M.F): Clockwise or Counter clockwise. The rotation direction is defined when facing the machine on the connection side. The phase sequence is set to clockwise and cannot be modified in the current version (grayed field). |
| 4 | Button to apply inputs. Pressing the enter key twice applies inputs too. |
| 5 | Button to restore default input values. Default values are those which define the winding architecture by using the automatic mode. |
| 6 | Icon to export winding data into *.txt or *.xlsx files. |
| 7 | Icon to export hairpin winding connection table into a *.xlsx file. This file can be shared and reloaded in another FluxMotor® session. |

4.3.5.3 Build a coil with expert mode



Building the winding architecture – Filling of the connection table

| | |
|----|---|
| 1 | Dialog box to define a connection table with expert mode. |
| 2 | Box to upload a connection table defined into a *.xlsx file. |
| 3 | Box to manually fill a connection table or modify an uploaded one from a *.xlsx file. |
| 4 | Selection of the number of layers. Number of layers are limited to 2 |
| 5 | Number of conductors per layer (This value must be even) |
| 6 | Number of slots per pole and per phase to set. No more than 2 times the number of slots per pole and per phase |
| 7 | Dynamic view of the hairpin winding updated in real time in function of the filling status of the connection table. |
| 8 | Area to customize the view. For each elementary coil set in parallel (A,B,C...): <ul style="list-style-type: none"> - Conductor number or current direction can be plotted - Hairpin or/and back-end connections can be displayed or not according to the selected elementary coils in the dialogue box |
| 9 | Icon to apply inputs and close the panel. |
| 10 | Icon to remove everything in the connection table (<i>Erase connection table data</i>). |
| 11 | Icon to cancel action and close the panel. |

Main rules to fill the connection table or to define a *.xlsx equivalent file:


- Define the number of layers, the number of conductors per layer and the number of slot/pole/phase according to the expected hairpin winding configuration
- Each parallel path (also called elementary coil) is characterized by a letter (A, B, C..., AA, AB,...)
- The parallel path A must begin by 1A+ or 1A-. 1 corresponds to the first conductor number. Each added conductor increment the conductor number by one.
 “+” or “-” correspond respectively to “clockwise” or “counterclockwise” direction of rotation of a parallel path (or part of a parallel path). Only the first conductor of a hairpin (odd number) can define the direction of rotation.
 The rotation direction is defined when facing the machine on the connection side.

Example:

How to define a parallel path composed of 16 conductors in which the first 8 rotates in the clockwise way (conductor 1 -> 8) and the other 8 rotates in the counterclockwise way (conductor 9 -> 16)?

The first conductor of the first 8 conductors must be defined as "1A+" to rotate in the clockwise direction.

Then the first conductor of the last 8 conductors must be defined as "9A-" to rotate in the counterclockwise direction.



4.4 Hairpin coil design - Inputs

4.4.1 Overview - Definitions

| Definition of the hairpin coil | | |
|--------------------------------|---|--|
| 1 | Selection of the STATOR subset: WINDING panel (Click on the icon WINDING). | |
| 2 | Selection of hairpin winding technology. | |
| 3 | Coil settings allow describing the coil composition (wires dimensions mainly) | |
| 4 | Description of the coil dimensions (Width, height, inter wire space). | |


The following inputs define the coil and how is filled the slots

| Label | Symbol | Tooltip, note, formula |
|------------------|------------|--|
| Wire width | W_{wire} | Wire width (without insulation), for rectangular shape wire |
| Wire height | H_{wire} | Wire height (without insulation), for rectangular shape wire |
| Inter-wire space | $w//w$ | Minimum distance between wires (with or without insulation) to be considered for modelling inside the Flux® 2D environment. This parameter allows getting a better wire distribution inside the slot. |


4.4.2 Relevance of the slot filling

When the number of wires (induced by the number of conductors per layer and the number of layers) are higher than allowed by the slot free area, the wires are grayed in the slot filling view. This is to inform the user that the number of wires must be decreased, so, with hairpin technology, the number of conductors per layer.

In that case, the design of the winding is not possible; the machine cannot be built or tested.




Motor Factory Design environment button and winding icon in the Stator section are colored in red. This means that there exist a fault in the design, which must be corrected.



The tests cannot be performed; the tooltip message indicates that the slot filling is not valid, and the user must modify the slot filling parameters to unlock the test.

At the same time, a warning message indicates that there is not enough space for the specified number of wires. The allowed number of wires are mentioned in comparison with the targeted ones.



4.5 Hairpin winding insulation design - Inputs

4.5.1 Overview - Definitions

Here are all the available insulation types.

| Label | Symbol | Tooltip, note, formula |
|-----------------------|--------|---|
| Wire | * | Insulation thickness of the wire |
| Liner | * | Insulation thickness of the liner. |
| Phase separator | * | Insulation thickness of the phase separator. |
| Impregnation | * | Insulation spread inside the slot. |
| Impregnation goodness | * | Quality of impregnation (percentage of winding impregnation). |

4.5.2 Illustrations for rectangular shape type wire




Illustration of winding insulation for rectangular shape type wire

| | |
|---|---|
| 1 | Insulation thickness of the wire |
| 2 | Insulation thickness of the liner |
| 3 | Insulation thickness of the phase separator |
| 4 | Presence of impregnation |

4.6 End winding design of hairpin winding – Inputs

4.6.1 Overview - definitions

This part characterizes the end-winding and the resulting conductor dimensions.
For additional information refer to the sections dedicated to the coil and conductor settings and End-winding topology

| Label | Symbol | Tooltip, note, formula |
|---------------------------|--------|--|
| End-winding topology | * | End-winding topology: Y-shape only |
| C.S. total extension | * | Connection side total extension. |
| C.S. straight extension | * | Connection side straight extension |
| O.C.S. total extension | * | Opposite connection side total extension. |
| O.C.S. straight extension | * | Opposite connection side straight extension. |

4.6.2 End-winding topology – Y-Shape

One topology is available: Y-shape end-winding.

WINDING

ClassicalHairpin

WindingCoilInsulationEnd wind.

END WINDING

| | |
|-----------------------------|--------|
| C.S. extension (mm) | 14.971 |
| O.C.S. extension (mm) | 14.971 |
| C.S. total extension (mm) | 26.416 |
| O.C.S. total extension (mm) | 26.416 |

Opposite Connection Side

Connection Side

57

57

3

4

8

6

5

Slot Upper part

Slot Bottom part

Slot pitch

Building the winding – End-winding topology and dimensions

| | |
|---|--|
| 1 | Selection of the Hairpin environment |
| 2 | Selection of the END-WINDING tab. |
| 3 | Straight extension of the Y-Shape end-winding topology = User input parameter. |
| 4 | Total extension of the Y-Shape end-winding topology = User input parameter. |
| 5 | Definition of the connection side straight extension (ref. 3). |
| 6 | Definition of the opposite connection straight extension (ref. 3). |
| 7 | Definition of the connection side total extension (ref. 4). |
| 8 | Definition of the opposite connection side total extension (ref. 4). |

4.7 Calibration factors definition - Inputs

4.7.1 Overview - Definitions

| Label | Symbol | Tooltip, note, formula |
|-------------------------------|--------|---|
| Ref. temperature | * | <p>The reference temperature. First, resistance values are computed by considering a temperature equal to 20°C. However, the user can also define his own reference temperature to compute the corresponding phase resistance and Line-Line resistance values.</p> <p>Note: This reference temperature is used only in the winding design environment. The test temperatures are defined in the test settings (refer to TEST chapter).</p> |
| Winding resistance factor | * | Setting of the "Resistance factor". It allows adjusting computation result of resistance with resistance measurement. Thus, the resulting phase resistance value is considered. |
| End winding inductance factor | * | Setting of the "Inductance factor". It allows modifying the computation result of end-winding inductance. Thus, the resulting end-winding inductance value is considered. |
| Ref. max. Line-Line voltage | Umax | Reference maximum Line-Line voltage. It allows evaluating the voltage drop between the conductors. |
| Voltage drop limit | * | Voltage drop limit between 2 superimposed conductors. This limit is given to better visualize the voltage threshold which shall not be exceeded (see the displaying of colored fields in the table). |

4.8 Potting design – Inputs

4.8.1 Overview - Definitions

"Potting" section is available only when the housing is defined with a frame (circular or square shape).
Please refer to section **2.7 (Potting design – Inputs)** since it has the same definition as classical winding topology.

5 HAIRPIN WINDING OUTPUTS

5.1 Characteristics

5.1.1 Winding

| Label | Symbol | Tooltip, note, formula |
|----------------------------------|---------------------|--|
| No. phases | m | Number of phases |
| No. poles | p | Number of rotor pole pairs. 2p = number of poles. |
| No. slots | Nslots | Number of stator slots |
| No. parallel paths | P _{paths} | Number of parallel paths (all modes). |
| No. Layers | N _{layers} | Number of layers - 1 or 2. |
| No. conductors per layer | | Number of conductors per layer |
| Layer shift | | Layer shift in number of slot pitch (Only available with 2 layers) |
| Coil layout | * | Coil layout inside the slot – Full or Superimposed |
| Winding connection | Connect | Winding connection (Y – Wye or Δ - Delta) |
| Winding type | * | The winding type: Wave |
| Current balance of parallel path | | Current balance of parallel path – Yes or No |
| No. slots / pole / phase | q | Number of slots per pole and per phase. $q = \frac{N_{slots}}{2p \times m}$ <p>(p is the number of pole pairs and m the number of phases)</p> |
| Pole pitch | τ_{pole-z} | $\tau_{pole-z} = \frac{No.slots}{2p}$ (Nslots = number of slots and p= number of pole pairs) |
| Phase sequence | * | Phase sequence i.e. rotation direction of the Magneto-Motive Force (M.M.F.): Clockwise or Counterclockwise (C. Clockwise). The rotation direction is defined when facing the machine on the connection side. |
| Coil pitch | τ_{coil} | The number of slot pitch between coil input and coil output is equal to the pole pitch for Auto, Easy and Advanced mode. For Expert mode, it is not computed because the coil pitch can be equal to different values. |

5.1.2 Winding factors (Fundamental)

Only winding factors corresponding to the fundamental signals are listed below.

| Label | Symbol | Tooltip, note, formula |
|---------------------|-------------|---|
| Winding factor | K_W | Winding factor: $K_W = K_{Dist} \times K_{Pitch} \times K_{Skew}$ |
| Distribution factor | K_{Dist} | Distribution factor. |
| Pitch factor | K_{Pitch} | Pitch factor. |
| Skew factor | K_{Skew} | Note: Skew factor is computed when the skewing of the stator slots is considered. Without slot skewing this factor is always equal to 1. |

For unbalanced hairpin configurations, as these results are not relevant, they are not computed and “-” is displayed instead. Unbalanced hairpin configurations are characterized by at least one parallel path which is different in term of voltage and impedance from the other parallel paths.

5.1.3 Coil

| Label | Symbol | Tooltip, note, formula |
|-------------------------------|------------------------|---|
| No. turns per coil | Turns | Number of turns per coil is always 1, because a hairpin is defined as a coil |
| No. turns in series per phase | N_{turns} | Number of turns in series per phase $N_{turns} = \frac{N_{conductor\ per\ parallel\ path}}{2}$ |
| No. conductors per phase | $N_{conductors/phase}$ | $N_{conductors/phase} = N_{conductor\ per\ parallel\ path} * N_{Parallel\ path}$ |

5.1.4 Lengths

Please refer to section 3.1.4 for more information about “**Lengths**” since it’s the same as Classical winding topology.

5.1.5 Areas in slot

Please refer to section 3.1.5 for more information about “**Areas in slot**” since it’s the same as Classical winding topology.

5.1.6 Fill factors

Please refer to section 3.1.6 for more information about “**Fill factors**” since it’s the same as Classical winding topology.

5.2 Slot filling

The slot filling result gives the user a realistic view of the filling of the slot in function of the setting options.
For additional information, please refer to 4.4 Hairpin coil design - Inputs.

5.3 Resistances

5.3.1 Resistances – Resistance at 20°C and at ref. temperature

| Label | Symbol | Tooltip, note, formula |
|---|--------|-----------------------------------|
| Phase resistance | * | Phase resistance |
| Line-Line resistance | * | Line-Line resistance |
| Parallel path number | | Number of parallel paths |
| Parallel path resistance | | Value of parallel path resistance |
| Winding straight part resistance | * | |
| End-winding resistance | * | |
| Connection side end-winding resistance | * | |
| Opposite connection side end-winding resistance | * | |
| | | |

Note 1: The reference temperature is a user input parameter defined in the winding – X-Factor tab.

Note 2: The connection side end-winding resistance considers the additional length corresponding to the connections between coils.

Note 3: For each parallel path, the resistances are computed and displayed for the winding straight part, the end-winding part (at connection side and at opposite connection side)

5.4 Inductances


| Label | Symbol | Tooltip, note, formula |
|----------------------|--------|--|
| Phase | | Phase inductance |
| Parallel path number | | Number of parallel paths |
| End winding | * | Total end winding inductance (including the two sides of the machine). |
| C.S. end winding | * | Connection side end winding inductance. |
| O.C.S. end winding | * | Opposite connection side end winding inductance. |

Note: For each parallel path, the end winding inductances are computed and displayed for the Connection Side and for the Opposite Connection Side.

5.5 Masses and costs

For additional information, refer to section 3.5 dedicated to masses and costs since it's the same as Classical winding topology.

5.6 Visualization of the winding architecture



5.7 Magneto-Motive Force analysis

For additional information, refer to section 3.7 dedicated to MMF analysis since it's the same as Classical winding topology.

5.8 Quality criteria

5.8.1 Winding factors


For additional information, refer to section 3.8 dedicated to the **winding factor** since it's the same as Classical winding topology.

For unbalanced hairpin configurations, as the results are not relevant, therefore, they are not computed and displayed.

Note, the unbalanced hairpin configurations are characterized by at least one parallel path which is different in term of voltage and impedance from the other parallel paths.

5.8.2 Slot star

The Slot star represents the total vectorial sum of voltages, at the ends of each coil, for each parallel path.
A slot star is computed and displayed for each parallel path.




Note: Definition of Strong and weak balance are done below

5.8.3 Parallel paths

For each slot per pole and per phase of each parallel path, the number of conductors in each conductor layer is computed and displayed in a table

The three kinds of possible configurations in term of electrical current in parallel paths are illustrated below: Strong balance, weak balance and unbalance



1

| Current balance of parallel paths | | | | | | | | | |
|-----------------------------------|-------|-------|-------|-------|-------|-------|-------|-------|--|
| | // 1 | | // 2 | | // 3 | | // 4 | | |
| | SPP 1 | SPP 2 | SPP 1 | SPP 2 | SPP 1 | SPP 2 | SPP 1 | SPP 2 | |
| Full: C1 | 2 | 0 | 2 | 0 | 0 | 2 | 0 | 2 | |
| Full: C2 | 2 | 0 | 2 | 0 | 0 | 2 | 0 | 2 | |
| Full: C3 | 0 | 1 | 0 | 2 | 2 | 1 | 2 | 0 | |
| Full: C4 | 0 | 1 | 0 | 2 | 2 | 1 | 2 | 0 | |




| | 1// | 2// | 3// | 4// |
|-----------|-------------|-------------|-------------|-------------|
| | SPP1 + SPP2 | SPP1 + SPP2 | SPP1 + SPP2 | SPP1 + SPP2 |
| Full : C1 | 2 | 2 | 2 | 2 |
| Full : C2 | 2 | 2 | 2 | 2 |
| Full : C3 | 1 | 2 | 3 | 2 |
| Full : C4 | 1 | 2 | 3 | 2 |

Current balance of parallel paths – Unbalance case example

| | |
|---|---|
| 1 | Layer of conductors |
| 2 | <p>Balance analysis classification:</p> <ul style="list-style-type: none"> - When the same number of conductors are displayed in all the cells, a “strong balance hairpin configuration” is obtained. This is the best winding design configuration. - If for each parallel path and all layers of conductors the sums of conductors are the same, a “weak balance hairpin configuration” is probably obtained (to be confirmed with the slot star if all the circles are well superimposed). - If for each parallel path and all layers of conductors the sums of conductors are different, an “unbalance hairpin configuration” is obtained. |

5.8.4 Voltage drop



6 FIELD WINDING

6.1 Overview

This kind of winding architecture is used to build the rotor poles of the wound field synchronous machines.

The rotor field winding has a lot of similarities with the 3-phase winding. Therefore, in each sub-section of the Rotor Winding context, only the differences compared to the 3-phase winding are mentioned. For further information regarding basic knowledge and terminology about electrical winding, please refer to the user help guide: "Windings" which is dedicated to the winding design General user information.

Here is the homepage for the design of the rotor winding.

| ROTOR WINDING design area | |
|---------------------------|--|
| 1 | Selection of the ROTOR subset: WINDING panel (click on the icon WINDING) |
| 2 | A section scrolling bar allows choosing the section in which user inputs are defined. Scrolling selection bar where Winding architecture, Coil, Insulation, End-winding, X-Factor and Potting sections can be selected |
| 3-4 | Winding input parameter panel dedicated for designing of the winding architecture (mainly the number of parallel paths) |
| 5 | Once a winding is defined, the corresponding results are automatically displayed in the form of a winding report. Visualization of the winding characteristics (inputs, settings, materials, etc) is possible. Scrollbars allow browsing the whole document rapidly and give an overview of all the results. Using scrollbars, complete data can be accessed and visualized. |
| 6 | Shortcuts to easily navigate in the output sections |

6.1.1 Winding Architecture

For the pole winding, the coils are wound concentrically around each pole. They are then connected in serial or in parallel. This architecture is simple and requires only one parameter regarding the number of parallel paths.

WINDING

Winding

Coil

Insulation

End wind.

INPUTS

No. parallel paths1

✓

↺

📄

1

2

4

3

Building the winding architecture

| | |
|---|--|
| 1 | Number of parallel paths: The possible numbers of parallel paths are automatically computed and proposed to the user. When the user selects the number of parallel paths, the connections on the winding scheme are automatically updated. See examples below. |
| 2 | Button to apply inputs. Pressing the enter key twice applies inputs too. |
| 3 | Button to restore default input values. Default values are those that defines the winding architecture by using the automatic mode. |
| 4 | Icon to export winding data into a text file |

6.1.1.1 Parallel paths

1

INPUTS

No. parallel paths1

✓

↺

2

INPUTS

No. parallel paths4

✓

↺

×

⊙

⊙

×

×

⊙

⊙

×

×

⊙

⊙

×

×

⊙


⊙

×

Building the winding architecture – The number of parallel paths is represented in the winding scheme

| | |
|---|---|
| 1 | Example where the No. parallel paths is equal to 1. |
| 2 | Example where the No. parallel paths is equal to 4. |


Proprietary Information of Altair Engineering



6.1.2 Winding – Coil

This section is the same as of 3-Phase winding, please refer to the user help guide: “MotorFactory_Winding” for further technical details about:

- Wire topologies
- Filling methods
- Grouping methods
- Wire dimensions




| Definition of the coil – Case of Circular wires | |
|---|---|
| 1 | Selection of the STATOR subset: WINDING panel (click on the icon WINDING) |
| 2 | Coil settings allow the user to describe the coil composition (turns, wires, and dimensions) and how to fill the slot. |
| 3 | Definition of the wire topology, Circular or Rectangular |
| 4 | Choice of the method to fill the slot: Three ways are allowed to fill the slot: Orthocyclic, Random, and Layer. See the illustrations in the referent document dedicated to the winding. |
| 5 | Choice of the method to group the elementary wires. Three ways allow to fill the slot: Grouped, Horizontal, Vertical. See the illustrations in the referent document dedicated to the winding. |
| 6 | Description of the coil (turns, wires in hand) and dimensions of elementary wires |

Note: The rotor windings are described in the same way as for the stator winding coils. For additional information, please refer to the section "Coil design" in the section "Windings" above.


Compared to the 3-Phase Winding, the only difference in the insulation section is that for the pole DC winding, there is no phase separator. Please refer to the user help guide dedicated to the winding for further technical details about:

- Types of insulators
- Impregnation



6.1.3.1 Liner thickness adjustment via part definition

The liner thickness is constant on all sides of the coil area which is defined by the part definition. The thickness of liner on each side can be adjusted by adding insulation regions to the pole part. A typical example can be found in the part isp_CB0000_OC00.



POLE : isp_CB0000_OC00

Design Skew

Pole shape


| INPUTS | |
|-------------------------------------|-----------|
| HPS (mm) | 19.833 |
| WPS (mm) | 87.45 |
| WPSR | 0.8 |
| RPS1 (mm) | 19.999 |
| WPB (mm) | 31.8 |
| HCOIL (mm) | 23.8 |
| WCOIL (mm) | 9.54 |
| WISOB (mm) | 7.95 E-1 |
| LISOS (mm) | 7.95 E-1 |
| WISOS (mm) | 7.933 E-1 |
| LISOY (mm) | 7.95 E-1 |
| WISOY (mm) | 7.933 E-1 |
| Width of isolation at the yoke (mm) | 2.385 |

Definition of liner thickness via part definition – Example with isp_CB0000_OC00

| | |
|---|--|
| 1 | The isp_CB0000_OC00 part can be found in the isp_CstBent library |
| 2 | The parameters, such as WISOY allow adjusting the isolation thickness of the winding on the yoke side. Use WISOB and WISOS to adjust the isolation thickness on the pole body and pole shoe sides. |
| 3 | The arrow shows the dimension corresponding to WISOY |

6.1.4 Winding – End Winding

Note: Compared to the 3-Phase Winding, the only difference in the insulation section is that for pole DC winding, there is only one type of end winding, which is the U-shape end winding. Please refer to the user help guide: “Windings” for further technical details about the topology of end winding and its dimensions.



SECTIONS

Configuration

Inputs Settings

Materials

Main results

Characteristics Slot filling

Resistances Inductances

Masses Costs

Views

Layout

Radiat

Axial

ROTOR - CLASSICAL WINDING

View Datasheet

WINDING

Winding Coil Insulation End wind

END WINDING


| | |
|-----------------------------|------|
| C.S. extension (mm) | 20.0 |
| O.C.S. extension (mm) | 20.0 |
| C.S. total extension (mm) | 30.0 |
| O.C.S. total extension (mm) | 30.0 |

Definition of the end winding

| | |
|---|--|
| 1 | End winding settings allow the user to describe the end winding dimensions. |
| 2 | The axial view of the machine allows to see each dimension change of the end winding; the Connection Side (C.S.) is indicated by the yellow lightning. |
| 3 | The parameters to adjust the end winding dimensions |

6.1.5 Winding – Calibration factor

By using the parameters in the X-factor section, the resistance of the winding and the inductance of the end winding can be adjusted to match their measured values at a given temperature.



Building the winding – X-Factor = Calibration factors

| | |
|---|---|
| 1 | Selection of the X-FACTOR section. |
| 2 | Setting of the “Resistance factor”. It allows adjusting the computation result of resistance. Thus, the resulting phase resistance value is considered. |
| 3 | Setting of the “Inductance factor”. It allows modifying the computation result of end-winding inductance. Thus, the resulting end-winding inductance value is considered. |
| 4 | The reference temperature: First, resistance values are computed by considering a temperature equal to 20°C (5). However, the users can also define their own reference temperature to compute the corresponding phase resistance and Line-Line resistance values. |
| 5 | Resistance values for a reference temperature equal to 20°C. |

7 DC WINDING

7.1 Overview


This kind of winding architecture is used by DC machines to define rotor winding.

The DC winding has a lot of similarities with the 3-phase winding but also many specific traits when referring to architecture.

Therefore, only the architecture is described in this section since the coil, insulation, end-winding and x-factor tabs does not have any important modification when compared with the 3-phase classical winding.

For further information regarding basic knowledge and terminology about electrical winding, please refer to the previous sections which is dedicated to the winding design general user information.

Here is the homepage for the design of the rotor winding.



WINDING design area – Overview

| | |
|-------------|---|
| 1 | Selection of the ROTOR subset: WINDING panel (Click on the icon WINDING) |
| 2 | All the required user inputs to define the winding are available in the "WINDING" panel (right part). |
| 3 | Once a winding is defined, the corresponding results are automatically displayed in the form of a winding report. Visualization of the winding characteristics (inputs, settings, materials, etc) are possible. Scrollbars allow browsing the whole document rapidly and giving an overview of all the results. Using scrollbars, complete data can be accessed and visualized. |
| 4 | Shortcuts for displaying the corresponding section of the winding report. |
| 5 | A section scrolling bar allows choosing the section in which user inputs are defined. Scrolling selection bar where Winding architecture, Coil, Insulation, End-winding and X-Factor sections can be selected |
| 6 | Three modes of winding allow to define and build the winding architecture . |
| Auto | Automatic mode, used as default. |
| Easy | Easy mode, to choose solution among those FluxMotor® proposes. |
| Adv. | Advanced mode, to allow the user to define any specific input parameters. |
| 7 | User input parameter fields to enter the values according to the considered mode. |

7.2 Winding Architecture - Inputs


7.2.1 Overview – Definitions

A DC winding is formed by as many individual coils as the number of slots of the machine. All these coils are identical except for an angular shift. Since the coils have an input slot and an output one, a slot will always have two coils wound inside it.

A key characteristic of a DC winding is that, unlike the 3-phase one, a coil is characterized (other by its input and output slots) by the two commutator segments connected to it (one for the input side and a second for the output side). These commutator segments will connect the coil to the brushes and, therefore, to the DC source feeding the machine.

That means that two main variables are needed to fully identify a coil:

- The throw – The coil pitch number of slot pitch between coil input and coil output.
- The commutator pitch: number of commutator segments between the segment connected to the coil input and the segment connected to the coil output.



These two parameters are not chosen randomly but to optimize the electromotive force. Two main types of winding exist: wave winding and lap winding.

- **Lap winding:** The ends of one coil are connected to consecutive commutation segments (i.e., the commutator pitch absolute value is equal to 1 for simplex winding)
- **Wave winding:** The ends of one coil are connected to commutator segment separated by an angular distance as close as two pole pitch as possible (for simplex winding)

For both winding types, the throw is usually as close as possible to a pole pitch.

Another two important concepts that define a DC winding and are applicable to both wave and lap windings, are the plex and the coil connection.

- The plex defines the number of commutator segments in contact with the same brush at a given time. It has a great influence on the number of parallel paths and, therefore, on the machine back EMF and the maximum current.
- The coil connection can be progressive and regressive: In a progressive connection the commutator segments are connected following the same direction as the winding (i.e., commutator pitch is positive) while in a regressive connection the commutator segments are connected following opposite direction as the winding (i.e., commutator pitch is negative).

More information about these variables is included in the next sections.

7.2.2 Automatic mode

7.2.2.1 User input parameters

No parameters are needed for the automatic mode.

7.2.2.2 Building the winding architecture – Automatic mode – Main principles

The automatic mode always creates the most basic winding corresponding to the number of poles and slots defining the machine topology. This scheme corresponds to a simplex lap winding with progressive connection. Values for throw and commutator pitch are defined in the table below.

| Basic winding variables | Symbol | Value in easy mode |
|-------------------------|----------------|---|
| Throw (coil pitch) | * | round (number of slots / number of poles) |
| Commutator pitch | Y _c | 1 |

WINDING

Scheme

Coil

Insulation

End wind.

Definition mode

Auto

Easy

Adv.

1

2

3

WINDING

Scheme

Coil

Insulation

End wind.

Definition mode

Auto

Easy

Adv.

INPUTS

Winding type

Lap

Plex

Simplex

Coil connection

Progressive

✓

↺

Building the winding architecture - **Automatic** mode and equivalence with the **Easy** mode

1

Selection of **Automatic** mode for building the winding architecture.


2

Equivalence between auto and easy modes. More information about the definition of the winding will be included in "Easy mode" section

3

Icon to export winding data into a text file

Proprietary Information of Altair Engineering




7.2.3 Easy mode

7.2.3.1 User input parameters

| Label | Symbol | Tooltip, note, formula |
|-----------------|--------|--|
| Winding type | * | Lap or wave |
| Plex | * | Number of different paths defined by the commutator / brushes contacts. It can be simplex, duplex or triplex |
| Coil connection | * | Progressive or regressive |

7.2.3.2 Building the winding architecture – Easy mode – Main principles



Building the winding architecture - **Easy** mode

| | |
|---|---|
| 1 | Selection of the Easy mode for building the winding architecture. |
| 2 | Selection of winding type. Lap: The ends of one coil are connected to consecutive commutation segments (i.e., the commutator pitch absolute value is equal to 1 for simplex winding) Wave: The ends of one coil are connected to commutator segment separated by an angular distance as close as two pole pitch as possible (for simplex winding) |
| 3 | Selection of the plex. The plex is a measure of how many commutator segments can touch a particular brush at the same time. The number of parallel paths in the machine circuit is directly proportional to its plex. Even if there is not a theoretical limitation to its value, for practical designs three plex are considered: simplex (plex=1), duplex (plex=2) and triplex (plex=3). |
| 4 | Selection of coil connection: Progressive or regressive Progressive connection: Commutator segments are connected following the same direction as winding (i.e., commutator pitch is positive). Regressive connection: Commutator segments are connected following opposite direction as winding (i.e., commutator pitch is negative). Illustration of these two types of winding is given in next sections. |
| 5 | Icon to restore default input values. Default values are those which define the winding architecture by using the automatic mode. |
| 6 | Icon to apply inputs. Pressing the enter key twice applies inputs too. |
| 7 | Icon to export winding data into a text file |

7.2.3.3 Winding type

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

Definition mode

AutoEasyAdv

INPUTS

Winding typeLap

PlexSimplex

Coil connectionProgressive

2

3

4

5

6

7

8

9

10

11

12

13

14

15

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

Definition mode

AutoEasyAdv

INPUTS

Winding typeWave

PlexSimplex

Coil connectionProgressive

✓

↺

Winding type – Graphical example

1Lap winding example

2Wave winding example

7.2.3.4 Plex

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

2

3

4

5

6

7

8

9

10

11

12

13

14

15

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

1

2

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

1

2

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

1


2

Plex – Graphical examples for a lap progressive winding

1Simplex winding

2Duplex winding

7.2.3.5 Coil connection




7.2.4 Advanced mode

7.2.4.1 User input parameters


| Label | Symbol | Tooltip, note, formula |
|------------------|--------|---|
| Throw | * | It is the coil pitch = number of slot pitches between coil input and coil output |
| Commutator pitch | Y_c | Number of commutator segments between the segment connected to the coil input and the segment connected to the coil output. |
| Coil layout | * | Coil layout inside the slot –Superimposed or Adjacent |

7.2.4.2 Building the winding architecture – Advanced mode – Main principles



Building the winding architecture - **Advanced** mode

| | |
|---|--|
| 1 | Selection of the Advanced mode for building the winding architecture. |
| 2 | Selection of the thrown (coil pitch) The proposed solutions depend on the number of slots and the number of poles. $\text{Throw} \leq \text{ceil}(\text{number of slots} / \text{number of poles})$ |
| 3 | Commutator pitch. Only the options compatible with a valid lap/wave winding are offered. |
| 4 | Definition of the coil layout i.e. how the coil sections are distributed into the slot. The two possible choices are: <ul style="list-style-type: none"> Superimposed = At least two superimposed coils into one slot Adjacent = At least two adjacent coils into one slot By default, the superimposed option is selected. |
| 5 | Icon to restore default input values. Default values are those which define the winding architecture by using the automatic mode. |
| 6 | Icon to apply inputs. Pressing the enter key twice applies inputs too. |
| 7 | Icon to export winding data into a text file |



7.2.5 Winding Architecture – Outputs

Outputs are quite like 3-phase winding, but some specific parameters arise when dealing with DC machine winding. For shake of completeness the parameters are listed in the tables below.

7.2.5.1 Characterization - Winding

| Label | Symbol | Tooltip, note, formula |
|--------------------|---------------------|--|
| No. poles | p | Number of rotor pole pairs. 2p = number of poles. |
| No. slots | Nslots | Number of stator slots |
| No. Layers | N _{layers} | Number of layers – For a DC winding it is always equal to 2 |
| Winding type | * | The winding type: Lap or wave |
| Plex | | The plex (simplex, duplex or triplex) |
| Coil connection | * | Connection type: Progressive or regressive Progressive connection: Commutator segments are connected following the same direction as winding (i.e., commutator pitch is positive). Regressive connection: Commutator segments are connecting following opposite direction as winding (i.e., commutator pitch is negative). |
| Commutator pitch | Y _c | Number of commutator segments between the segment connected to the coil input and the segment connected to the coil output. |
| No. parallel paths | P _{paths} | Number of parallel paths. For a wave winding it is equal to twice the plex. For a lap winding it is equal to number of poles * plex |
| Coil layout | * | Coil layout inside the slot – Full, Superimposed or Adjacent. |
| Throw (coil pitch) | * | Number of slot pitch between coil input and coil output. |

7.2.5.2 Characterization - Coil

| Label | Symbol | Tooltip, note, formula |
|---------------------|--------------------|---|
| No. turns per coil | Turns | Number of turns per coil. |
| No. turns in series | N _{turns} | Number of turns in series $N_{turns} = \frac{N_{coils}}{2 \times P_{paths}}$ |
| No. conductors | N _{cond} | Total number of conductors $N_{coils} = 2 \times N_{slots} \times Turns$ |

7.2.5.3 Lengths

| Label | Symbol | Tooltip, note, formula |
|------------------------|--------|--|
| Total conductor length | * | Total conductor length. |
| Mean turn length | * | Mean turn length. |
| Coil connection length | * | Additional length corresponding to the connections between coils and commutator segments. |
| Axial overall length | * | Axial overall length. Length between the two extremities of the winding i.e. between connection side and opposite connection side. |


7.2.5.4 Areas in slot

| Label | Symbol | Tooltip, note, formula |
|---------------------------|-----------------|---|
| Conductive area | $A_{CondSlot}$ | Conductive area inside one slot. $A_{CondSlot} = A_{Cond} \times Turns$ |
| Conductor conductive area | A_{Cond} | $A_{Cond} = N_{wires} \times A_{wire}$ This area allows to compute the current density. |
| Wire conductive area | A_{wire} | Wire area (without insulation). |
| Slot area | A_{slot} | Slot area. |
| Insulation area | $A_{InsulSlot}$ | Insulation area inside one slot. One considers the slots of the machine where the number of coils are maximum. |
| Free area | A_{Free} | $A_{Free} = A_{slot} - A_{CondSlot} - A_{InsulSlot}$ |

7.2.5.5 Fill factors

| Label | Symbol | Tooltip, note, formula |
|-------------------|--------|---|
| Gross fill factor | * | Gross fill factor. Occupancy rate of the slot (conductive area only). $\frac{Conductor\ conductive\ area}{Slot\ area} \times 100$ |
| Net fill factor | * | Net fill factor. Occupancy rate of the slot (conductive area + insulation area). $\frac{Conductor\ conductive\ area + insulation\ area}{Slot\ area} \times 100$ |

7.2.5.6 Resistances

| Label | Symbol | Tooltip, note, formula |
|---|--------|--|
| Single coil resistance | * | Single coil resistance |
| Parallel path resistance | * | Resistance of one of the parallel paths |
| Total resistance | * | Total resistance of the machine at its terminals |
| Winding straight part resistance | * |  |
| End-winding resistance | * | |
| Connection side end-winding resistance | * | |
| Opposite connection side end-winding resistance | * | |
| | | |

Note 1: The reference temperature is a user input parameter defined in the winding – X-Factor tab.

Note 2: The connection side end-winding resistance considers the additional length corresponding to the connection between coils and commutator segments.

7.2.5.7 Inductances


| Label | Symbol | Tooltip, note, formula |
|--------------------|--------|--|
| End winding | * | Total end winding inductance (including the two sides of the machine). |
| C.S. end winding | * | Connection side end winding inductance. |
| O.C.S. end winding | * | Opposite connection side end winding inductance. |

7.2.5.8 Masses and costs

For additional information, refer to the sections dedicated to the coil and conductor settings and End-winding topology.

| Label | Symbol | Tooltip, note, formula |
|----------------------------|--------|---|
| Total | * | Total winding mass. |
| Electric conductor | * | Conductive part mass. |
| Total insulation | * | Total winding insulation mass (wire + conductor + coil insulation + liner + phase separator). |
| Wire insulation | * | Wire insulation. |
| Conductor insulation | * | Conductor insulation. |
| Coil insulation | * | Coil insulation. |
| Liner insulation | * | Liner insulation. |
| Phase separator insulation | * | Phase separator insulation. |
| Impregnation insulation | * | Impregnation insulation |
| Wedge insulation | * | Wedge insulation, only when the slot topology contains a wedge |

7.2.5.9 Visualization of the winding architecture



8 CHOICE OF WINDING MATERIALS

All the materials needed for building the winding (conductors and insulations) are distributed in the section "Materials" of the Motor Factory - Stator - Design environment.
All the materials are selected from the material database.